


LTC1727/LTC1728

ABSOLUTE MAXIMUM RATINGS (Notes 1, 2)

V_{CC3} , $V_{CC5}/V_{CC25}/V_{CC18}$, V_{CCA} -0.3V to 7V
RST -0.3V to 7V
COMP3, COMP25/COMP5
(MS8 and SO-8 Only) -0.3V to 7V

Operating Temperature Range
LTC1727/LTC1728E (Note 3) -40°C to 85°C
LTC1728H -40°C to 125°C
LTC1727I -40°C to 85°C
Storage Temperature Range -65°C to 150°C
Lead Temperature (Soldering, 10 sec) 300°C

PIN CONFIGURATION



ORDER INFORMATION

LEAD FREE FINISH	TAPE AND REEL	PART MARKING*	PACKAGE DESCRIPTION	TEMPERATURE RANGE
LTC1727EMS8-2.5#PBF	LTC1727EMS8-2.5#TRPBF	LTHY	8-Lead Plastic MSOP	-40°C to 85°C
LTC1727EMS8-5#PBF	LTC1727EMS8-5#TRPBF	LTHX	8-Lead Plastic MSOP	-40°C to 85°C
LTC1727ES8-2.5#PBF	LTC1727ES8-2.5#TRPBF	172725	8-Lead Plastic SO	-40°C to 85°C
LTC1727IS8-2.5#PBF	LTC1727IS8-2.5#TRPBF	727I25	8-Lead Plastic SO	-40°C to 85°C
LTC1727ES8-5#PBF	LTC1727ES8-5#TRPBF	17275	8-Lead Plastic SO	-40°C to 85°C
LTC1727IS8-5#PBF	LTC1727IS8-5#TRPBF	1727I5	8-Lead Plastic SO	-40°C to 85°C
LTC1728ES5-1.8#PBF	LTC1728ES5-1.8#TRPBF	LTPH	8-Lead Plastic SOT-23	-40°C to 85°C
LTC1728ES5-2.5#PBF	LTC1728ES5-2.5#TRPBF	LTIA	8-Lead Plastic SOT-23	-40°C to 85°C
LTC1728ES5-3.3#PBF	LTC1728ES5-3.3#TRPBF	LTYP	8-Lead Plastic SOT-23	-40°C to 85°C
LTC1728ES5-5#PBF	LTC1728ES5-5#TRPBF	LTHZ	8-Lead Plastic SOT-23	-40°C to 85°C
LTC1728HS5-5#PBF	LTC1728HS5-5#TRPBF	LTHZ	8-Lead Plastic SOT-23	-40°C to 125°C

Contact the factory for parts specified with wider operating temperature ranges. *The temperature grade is identified by a label on the shipping container.

[Tape and reel specifications](#). Some packages are available in 500 unit reels through designated sales channels with #TRMPBF suffix.

ELECTRICAL CHARACTERISTICS All except LTC1728-1.8/LTC1728-3.3. The ● denotes specifications which apply over the full operating temperature range, otherwise specifications are at $T_A = 25^\circ\text{C}$. $V_{CC3} = 3.3\text{V}$, $V_{CC5} = 5\text{V}$, $V_{CC25} = 2.5\text{V}$, $V_{CCA} = V_{CC3}$ unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS		MIN	TYP	MAX	UNITS
V _{RT3}	Reset Threshold V _{CC3}	V _{CC3} Input Threshold	●	3.036	3.086	3.135	V
V _{RT5}	Reset Threshold V _{CC5}	V _{CC5} Input Threshold (5V Version)	●	4.600	4.675	4.750	V
V _{RT25}	Reset Threshold V _{CC25}	V _{CC25} Input Threshold (2.5V Version)	●	2.300	2.338	2.375	V
V _{RTA}	Reset Threshold V _{CCA}	V _{CCA} Input Threshold	●	0.985	1.000	1.015	V
V _{CCOP}	V _{CC3} , V _{CC5} /V _{CC25} Operating Voltage	R _{ST} , COMP3, COMP5, COMP25 in Correct Logic State	●	1		7	V
V _{CCOPA}	V _{CC3} , V _{CC5} /V _{CC25} Operating Voltage	Minimum Supply Voltage to Guarantee COMPA in Correct Logic State	●		2	2.3	V
I _{VCC3}	V _{CC3} Supply Current	V _{CC5} /V _{CC25} > V _{CC3} V _{CC5} /V _{CC25} < V _{CC3} , V _{CC3} = 3.3V (Note 4)	● ●		1 10	2 20	μA μA
I _{VCC25}	V _{CC25} Supply Current	V _{CC25} < V _{CC3} , V _{CC25} = 2.5V (Note 4)	●		1	2	μA
I _{VCC5}	V _{CC5} Supply Current	V _{CC5} = 5V, V _{CC3} < V _{CC5}	●		10	20	μA
I _{VCCA}	V _{CCA} Input Current	V _{CCA} = 1V −40°C < T _A < 125°C	● ●	−15 −20	0 0	15 50	nA nA
t _{RST}	Reset Pulse Width	R _{ST} Low with 10k Pull-Up to V _{CC3} (Note 5) −40°C < T _A < 125°C	● ●	140 140	200	280 350	ms ms
t _{UV}	V _{CC} Undervoltage Detect to R _{ST} or COMPX	V _{CC5} , V _{CC25} , V _{CC3} or V _{CCA} Less Than Reset Threshold V _{RT} by More Than 1% (Note 5)			110		μs
V _{OL}	Output Voltage Low, R _{ST} , COMPX	I _{SINK} = 2.5mA, V _{CC3} = 3V, V _{CC5} /V _{CC25} = 0V I _{SINK} = 100μA, V _{CC3} = 1V, V _{CC5} /V _{CC25} = 0V I _{SINK} = 100μA, V _{CC3} = 0V, V _{CC5} /V _{CC25} = 1V I _{SINK} = 100μA, V _{CC3} = 1V, V _{CC5} /V _{CC25} = 1V	● ● ● ●		0.15 0.05 0.05 0.05	0.4 0.3 0.3 0.3	V V V V
V _{OH}	Output Voltage High, R _{ST} , COMPX (Note 6)	I _{SOURCE} = 1μA	●	V _{CC3} − 1			V
LTC1727-5/LTC1728-5 Only							
V _{OVR}	V _{CC5} Reset Override Voltage (Note 7)	Override V _{CC5} Ability to Assert R _{ST}		V _{CC3} ±0.025			V

LTC1727-5/LTC1728-5 Only

V_{OVR}	V_{CC5} Reset Override Voltage (Note 7)	Override V_{CC5} Ability to Assert $\overline{\text{RST}}$		$V_{CC3} \pm 0.025$		V
-----------	---	--	--	---------------------	--	---

LTC1728-1.8 The ● denotes specifications which apply over the full operating temperature range, otherwise specifications are at $T_A = 25^\circ\text{C}$. $V_{CC3} = 3\text{V}$, $V_{CC18} = 1.8\text{V}$, $V_{CCA} = V_{CC3}$ unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS		MIN	TYP	MAX	UNITS
V _{RT3}	Reset Threshold V _{CC3}	V _{CC3} Input Threshold	●	2.760	2.805	2.850	V
V _{RT18}	Reset Threshold V _{CC18}	V _{CC18} Input Threshold	●	1.656	1.683	1.710	V
V _{RTA}	Reset Threshold V _{CCA}	V _{CCA} Input Threshold	●	0.985	1.000	1.015	V
V _{CCOP}	V _{CC3} , V _{CC18} Operating Voltage	R _{ST} in Correct Logic State	●	1		7	V
I _{VCC3}	V _{CC3} Supply Current	V _{CC18} > V _{CC3} V _{CC18} < V _{CC3} , V _{CC3} = 3V (Note 4)	● ●	1 10		2 20	μA μA
I _{VCC18}	V _{CC18} Supply Current	V _{CC18} < V _{CC3} , V _{CC18} = 1.8V (Note 4)	●	1		2	μA
I _{VCCA}	V _{CCA} Input Current	V _{CCA} = 1V	●	−15	0	15	nA
t _{RST}	Reset Pulse Width	R _{ST} Low (Note 5)	●	140	200	280	ms
t _{UV}	V _{CC} Undervoltage Detect to R _{ST}	V _{CC18} , V _{CC3} or V _{CCA} Less Than Reset (Note 5) Threshold V _{RT} by More Than 1%		110			μs
V _{OL}	Output Voltage Low, R _{ST}	I _{SINK} = 2.5mA, V _{CC3} = 3V, V _{CC18} = 0V I _{SINK} = 100μA, V _{CC3} = 1V, V _{CC18} = 0V I _{SINK} = 100μA, V _{CC3} = 0V, V _{CC18} = 1V I _{SINK} = 100μA, V _{CC3} = 1V, V _{CC18} = 1V	● ● ● ●	0.15 0.05 0.05 0.05		0.4 0.3 0.3 0.3	V V V V
V _{OH}	Output Voltage High, R _{ST}	I _{SOURCE} = 1μA (Note 6)	●	V _{CC3} − 1			V

ELECTRICAL CHARACTERISTICS

LTC1728-3.3 The ● denotes specifications which apply over the full operating temperature range, otherwise specifications are at $T_A = 25^\circ\text{C}$. $V_{CC3} = 3.3\text{V}$, $V_{CC18} = 1.8\text{V}$, $V_{CCA} = V_{CC3}$ unless otherwise noted.

SYMBOL	PARAMETER	CONDITIONS		MIN	TYP	MAX	UNITS
V_{RT3}	Reset Threshold V_{CC3}	V_{CC3} Input Threshold	●	3.036	3.086	3.135	V
V_{RT18}	Reset Threshold V_{CC18}	V_{CC18} Input Threshold	●	1.656	1.683	1.710	V
V_{RTA}	Reset Threshold V_{CCA}	V_{CCA} Input Threshold	●	0.985	1.000	1.015	V
V_{CCOP}	V_{CC3} , V_{CC18} Operating Voltage	$\overline{\text{RST}}$ in Correct Logic State	●	1		7	V
I_{VCC3}	V_{CC3} Supply Current	$V_{CC18} > V_{CC3}$ $V_{CC18} < V_{CC3}$, $V_{CC3} = 3.3\text{V}$ (Note 4)	● ●		1 10	2 20	μA μA
I_{VCC18}	V_{CC18} Supply Current	$V_{CC18} < V_{CC3}$, $V_{CC18} = 1.8\text{V}$ (Note 4)	●		1	2	μA
I_{VCCA}	V_{CCA} Input Current	$V_{CCA} = 1\text{V}$	●	-15	0	15	nA
t_{RST}	Reset Pulse Width	$\overline{\text{RST}}$ Low (Note 5)	●	140	200	280	ms
t_{UV}	V_{CC} Undervoltage Detect to $\overline{\text{RST}}$	V_{CC18} , V_{CC3} or V_{CCA} Less Than Reset (Note 5) Threshold V_{RT} by More Than 1%			110		μs
V_{OL}	Output Voltage Low, $\overline{\text{RST}}$	$I_{\text{SINK}} = 2.5\text{mA}$, $V_{CC3} = 3.3\text{V}$, $V_{CC18} = 0\text{V}$	●		0.15	0.4	V
		$I_{\text{SINK}} = 100\mu\text{A}$, $V_{CC3} = 1\text{V}$, $V_{CC18} = 0\text{V}$	●		0.05	0.3	V
		$I_{\text{SINK}} = 100\mu\text{A}$, $V_{CC3} = 0\text{V}$, $V_{CC18} = 1\text{V}$	●		0.05	0.3	V
		$I_{\text{SINK}} = 100\mu\text{A}$, $V_{CC3} = 1\text{V}$, $V_{CC18} = 1\text{V}$	●		0.05	0.3	V
V_{OH}	Output Voltage High, $\overline{\text{RST}}$	$I_{\text{SOURCE}} = 1\mu\text{A}$ (Note 6)	●	$V_{CC3} - 1$			V

Note 1: Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. Exposure to any Absolute Maximum Rating condition for extended periods may affect device reliability and lifetime.

Note 2: All voltage values are with respect to GND.

Note 3: The LTC1727E/LTC1728E are guaranteed to meet specified performance from 0°C to 70°C and are designed, characterized and assured to meet the extended temperature limits of -40°C to 85°C but are not tested at these temperatures.










Note 4: Both V_{CC3} and $V_{CC5}/V_{CC25}/V_{CC18}$ can act as the supply depending on which pin has the greatest potential.

Note 5: Measured from when input passes through the input threshold (V_{RTX}) until $\overline{\text{RST}}$ or COMPX passes through 1.5V.

Note 6: The output pins $\overline{\text{RST}}$ and COMPX have internal pull-ups to V_{CC3} of typically $6\mu\text{A}$. However, external pull-up resistors may be used when faster rise times are required or for V_{OH} voltages greater than V_{CC3} .


Note 7: The V_{CC5} reset override voltage is valid for an operating range less than approximately 4.15V. Above this point the override is turned off and the V_{CC5} pin functions normally.

TYPICAL PERFORMANCE CHARACTERISTICS

V_{CCA} Input Current vs Input Voltage**V_{CCA} Threshold Voltage vs Temperature****Typical Transient Duration vs Comparator Overdrive****Reset Pulse Width vs Temperature****R_{ST}, COMPX I_{SINK} vs Supply Voltage****I_{VCC25} vs Temperature (LTC1727-2.5/LT1728-2.5)****I_{VCC3} vs Temperature (LTC1727-2.5/LTC1728-2.5/LTC1728-3.3)****I_{VCC3} vs Temperature (LTC1727-5/LTC1728-5)****I_{VCC5} vs Temperature (LTC1727-5/LTC1728-5)**


TYPICAL PERFORMANCE CHARACTERISTICS

**V_{CC25} Threshold Voltage
vs Temperature
(LTC1727-2.5/LTC1728-2.5)**




1727/28 G10

**V_{CC3} Threshold Voltage
vs Temperature
(All But LTC1728-1.8)**




1727/28 G11

**V_{CC5} Threshold Voltage
vs Temperature
(LTC1727-5/LTC1728-5)**




1727/28 G12

**I_{VCC18} vs Temperature
(LTC1728-1.8/LTC1728-3.3)**




1727/28 G13

**I_{VCC3} vs Temperature
(LTC1728-1.8)**




1727/28 G14

**V_{CC18} Threshold Voltage
vs Temperature
(LTC1728-1.8/LTC1728-3.3)**



1727/28 G15

**V_{CC3} Threshold Voltage
vs Temperature (LTC1728-1.8)**



1727/28 G16

PIN FUNCTIONS (LTC1727/LTC1728)

V_{CC3} (Pin 1/Pin 5): 3.3V Sense Input and Power Supply Pin. (3V Sense Input and Power Supply Pin for LTC1728-1.8.) This pin provides power to the part when the voltage on V_{CC3} is greater than the voltage on V_{CC5}/V_{CC25}/V_{CC18}. Bypass to ground with a $\geq 0.1\mu\text{F}$ ceramic capacitor.

V_{CC5} (Pin 2/Pin 4): 5V Sense Input and Power Supply Pin. This pin is used on the LTC1727-5/LTC1728-5 to provide power to the part when the voltage on V_{CC5} is greater than the voltage on V_{CC3}. Bypass to ground with a $\geq 0.1\mu\text{F}$ ceramic capacitor.

V_{CC25} (Pin 2/Pin 4): 2.5V Sense Input and Power Supply Pin. This pin is used on the LTC1727-2.5/LTC1728-2.5 to provide power to the part when the voltage on V_{CC25} is greater than the voltage on V_{CC3}. Bypass to ground with a $\geq 0.1\mu\text{F}$ ceramic capacitor.

V_{CC18} (Pin 2/Pin 4): 1.8V Sense Input and Power Supply Pin. This pin is used on the LTC1728-1.8/LTC1728-3.3 to provide power to the part when the voltage on V_{CC18} is greater than the voltage on V_{CC3}. Bypass to ground with a $\geq 0.1\mu\text{F}$ ceramic capacitor.

V_{CCA} (Pin 3/Pin 3): 1V Sense, High Impedance Input. If unused, it can be tied to either V_{CC3} or V_{CC5}/V_{CC25}/V_{CC18}.

GND (Pin 4/Pin 2): Ground.

COMP_A (Pin 5): V_{CCA} Comparator Output for the LTC1727. Active high, open-drain logic output with weak pull-up to V_{CC3}. Asserted when V_{CCA} is above V_{RTA}. Deasserted when V_{CCA} is below V_{RTA} or if both the V_{CC3} and V_{CC5} supply pins are too low to power the internal bandgap reference (typically $< 2.0\text{V}$). Can be pulled greater than V_{CC3} using an external pull-up.

R_{ST} (Pin 6/Pin 1): Reset Logic Output. Active low, open-drain logic output with weak pull-up to V_{CC3}. Can be pulled up greater than V_{CC3} when interfacing to 5V logic. Asserted when one or all of the supplies are below trip thresholds and held for 200ms after all supplies become valid.

COMP₅ (Pin 7): V_{CC5} Comparator Output for the LTC1727-5. Active high, open-drain logic output with weak pull-up to V_{CC3}. Asserted when V_{CC5} is above V_{RT5}. Can be pulled greater than V_{CC3} using an external pull-up.

COMP₂₅ (Pin 7): V_{CC25} Comparator Output for the LTC1727-2.5. Active high, open-drain logic output with weak pull-up to V_{CC3}. Asserted when V_{CC25} is above V_{RT25}. Can be pulled greater than V_{CC3} using an external pull-up.

COMP₃ (Pin 8): V_{CC3} Comparator Output for the LTC1727. Active high, open-drain logic output with weak pull-up to V_{CC3}. Asserted when V_{CC3} is above V_{RT3}. Can be pulled greater than V_{CC3} using an external pull-up.


BLOCK DIAGRAMS

The schematic diagram of the 1727 BD1 microcontroller shows the following internal components and connections:


- Inputs:**
 - Pin 1 (V_{CC3}) connects to the non-inverting input of the first comparator and the **POWER DETECT** block.
 - Pin 2 (V_{CC5}/V_{CC25}) connects to the inverting input of the second comparator.
 - Pin 3 (V_{CCA}) connects to the non-inverting input of the third comparator.
 - Pin 4 (GND) connects to the inverting input of the third comparator.
- Internal Blocks:**
 - POWER DETECT:** Receives input from Pin 1 and outputs to the non-inverting input of the first comparator.
 - BANDGAP REFERENCE:** Provides a reference voltage to the inverting input of the third comparator.
 - Three Comparators:** Each has a non-inverting (+) and inverting (-) input. Their outputs are connected to the inputs of an OR gate.
 - 200ms PULSE GENERATOR:** Receives input from the OR gate and outputs to a **200ms DELAY** block.
 - 200ms DELAY:** Outputs to the **RST** pin (Pin 6).
- Outputs:**
 - COMP3 (Pin 8):** Connected to the output of the first comparator.
 - COMP25/COMP5 (Pin 7):** Connected to the output of the second comparator.
 - RST (Pin 6):** Connected to the output of the 200ms delay block.
 - COMP4 (Pin 5):** Connected to the output of the third comparator.
- Output Drivers:** Each output pin (5, 6, 7, 8) has a push-pull driver consisting of an NPN transistor (emitter to GND, collector to pin) and a PNP transistor (emitter to V_{CC3} , collector to pin). Each PNP transistor has a $6\mu A$ current source connected to its base.

BLOCK DIAGRAMS

LTC1728-5/LTC1728-2.5/LTC1728-1.8/LTC1728-3.3



TIMING DIAGRAM

 V_{CC} Monitor Timing

APPLICATIONS INFORMATION

Supply Monitoring

The LTC1727 is a low power, high accuracy triple supply monitoring circuit with three monitor outputs and a 200ms microprocessor reset output.

The LTC1728 is a low power, high accuracy triple supply monitoring circuit with a single 200ms microprocessor reset output.

All three V_{CC} inputs must be above predetermined thresholds for reset not to be invoked. The LTC1727/LTC1728 will assert reset during power-up, power-down and brownout conditions on any one or all of the V_{CC} inputs.

Power Detect

The LTC1727/LTC1728 are powered from the 3.3V/3V input pin (V_{CC3}), the 1.8V input pin (V_{CC18}), the 2.5V input pin (V_{CC25}) or the 5V input pin (V_{CC5}), whichever pin has the highest potential. This ensures the part pulls the $\overline{RST}$ pin low as soon as either input pin is $\geq 1V$.

Power-Up

Upon power-up, either the $V_{CC5}/V_{CC25}/V_{CC18}$ or V_{CC3} pin, can power the part. This ensures that $\overline{RST}$ will be low when either $V_{CC5}/V_{CC25}/V_{CC18}$ or V_{CC3} reaches 1V. As long as any one of the V_{CC} inputs is below its predetermined threshold, $\overline{RST}$ will stay a logic low. Once all of the V_{CC} inputs rise above their thresholds, an internal timer is started and $\overline{RST}$ is released after 200ms.

$\overline{RST}$ is reasserted whenever any one of the V_{CC} inputs drops below its predetermined threshold and remains asserted until 200ms after all of the V_{CC} inputs are above their thresholds.

On the LTC1727, each of the comparator outputs will be low until the V_{CC} input that is monitored by that comparator rises above the appropriate predetermined threshold. The COMP3, and COMP5/COMP25 outputs are guaranteed to be in the correct logic state for either V_{CC3} or V_{CC5}/V_{CC25} greater than 1V. The COMPA output requires the internal bandgap reference to be valid before the correct logic state can be output. Therefore, the COMPA output will be held low until V_{CCA} is above 1V and V_{CC3} or V_{CC5}/V_{CC25} is greater than 2V (typ).

Power-Down

On power-down, once any of the V_{CC} inputs drop below its threshold, $\overline{RST}$ is held at a logic low. A logic low of 0.3V is guaranteed until both V_{CC3} and $V_{CC5}/V_{CC25}/V_{CC18}$ drop below 1V.

Glitch Immunity

The $\overline{RST}$ output of the LTC1727/LTC1728 have two forms of glitch immunity built in. First, the input monitors require the input voltage to transition at least 10% of the input threshold ($0.1 \cdot V_{RTH}$) below the input threshold for approximately 50 μ s in order to force the monitor output low. The duration of the transition must be longer for voltage transitions of lesser magnitude (see Figure 1). Secondly, the reset pulse width of approximately 200ms acts to debounce the $\overline{RST}$ output ensuring that the $\overline{RST}$ output will always be in the correct state.

The individual monitor outputs of the LTC1727 do not have hysteresis and will track the monitor inputs relative to the monitor's input threshold (V_{RTA} , V_{RT25} , V_{RT3} and V_{RT5}). A very slow moving input voltage with ripple riding on it may cause the individual monitor outputs (COMP_A, COMP₂₅, COMP₃ and COMP₅) to toggle on the ripple as the input voltage passes the input threshold. The slow response time of the LTC1727's input monitors has a tendency to integrate signals on the inputs improving their immunity to noise and ripple.




Figure 1. Transient Duration vs Comparator Overdrive

APPLICATIONS INFORMATION

Override Functions (5V Versions Only)

The V_{CCA} pin, if unused, can be tied to either V_{CC3} or V_{CC5} . This is an obvious solution since the trip points for V_{CC3} and V_{CC5} will always be greater than the trip point for V_{CCA} .

The V_{CC5} input trip point is disabled if its voltage is equal to the voltage on $V_{CC3} \pm 25\text{mV}$ and the voltage on V_{CC5} is less than 4.15V. In this manner, the LTC1727-5/LTC1728-5 will behave as a 3.3V monitor and V_{CC5} reset capability will be disabled.

The V_{CC5} trip point is reenabled when the voltage on V_{CC5} is equal to the voltage on $V_{CC3} \pm 25\text{mV}$ and the two inputs are greater than approximately 4.15V. In this manner, the part can function as a 5V monitor with the 3.3V monitor disabled.

When monitoring either 3.3V or 5V with V_{CC3} strapped to V_{CC5} (see Figure 2), the part determines which is the appropriate range. The part handles this situation as shown in Figure 3. Above 1V and below V_{RT3} , $\overline{\text{RST}}$ is held low. From V_{RT3} to approximately 4.15V the part assumes 3.3V supply monitoring and $\overline{\text{RST}}$ is deasserted. Above approximately 4.15V the part operates as a 5V monitor. In most systems the 5V supply will pass through the 3.1V to 4.15V region in <200ms during power-up, and the $\overline{\text{RST}}$ output will behave as desired. Table 1 summarizes the state of $\overline{\text{RST}}$ at various operating voltages with $V_{CC3} = V_{CC5}$.

Table 1. Override Truth Table ($V_{CC3} = V_{CC5}$)

INPUTS ($V_{CC3} = V_{CC5} = V_{CC}$)	$\overline{\text{RST}}$
$0\text{V} \leq V_{CC} \leq 1\text{V}$	—
$1\text{V} \leq V_{CC} \leq V_{RT3}$	0
$V_{RT3} \leq V_{CC} \leq 4.15\text{V}$	1
$4.15\text{V} \leq V_{CC} \leq V_{RT5}$	0
$V_{RT5} \leq V_{CC}$	1




Figure 2. Single Supply Monitor with Others Disabled




Figure 3. $\overline{\text{RST}}$ Voltage vs Supply Voltage

APPLICATIONS INFORMATION

Figure 4 contains a simple circuit for 5V systems that can't risk the $\overline{\text{RST}}$ output going high in the 3.1V to 4.15V range (possibly due to very slow rise time on the 5V supply). Diode D1 powers the LTC1728-5 while dropping $\approx 0.6\text{V}$ from the $\text{V}_{\text{CC}5}$ pin to the $\text{V}_{\text{CC}3}$ pin. This prevents the part's internal override circuit from being activated. Without the override circuit active, the $\overline{\text{RST}}$ pin stays low until $\text{V}_{\text{CC}5}$ reaches $\text{V}_{\text{RT}5} \approx 4.675\text{V}$. (See Figure 5.)




Figure 4. LTC1728-5 Monitoring a Single 5V Supply. D1 Used to Avoid $\overline{\text{RST}}$ High Near 3.1V to 4V (See Figure 3)

LTC1727-2.5/LTC1728-2.5/LTC1728-1.8/LTC1728-3.3 Override Functions

The V_{CCA} pin, if unused, can be tied to either $\text{V}_{\text{CC}3}$ or $\text{V}_{\text{CC}25}/\text{V}_{\text{CC}18}$. This is an obvious solution since the trip points for $\text{V}_{\text{CC}3}$ and $\text{V}_{\text{CC}25}/\text{V}_{\text{CC}18}$ will always be greater than the trip point for V_{CCA} . Likewise, the $\text{V}_{\text{CC}25}/\text{V}_{\text{CC}18}$, if unused, can be tied to $\text{V}_{\text{CC}3}$. $\text{V}_{\text{CC}3}$ must always be used. Tying $\text{V}_{\text{CC}3}$ to $\text{V}_{\text{CC}25}/\text{V}_{\text{CC}18}$ and operating off of a 2.5V/1.8V supply will result in the continuous assertion of $\overline{\text{RST}}$.





Figure 5. $\overline{\text{RST}}$ Output Voltage Characteristics of the Circuit in Figure 4


TYPICAL APPLICATIONS

Triple Supply Monitor (3.3V, 5V and Adjustable)




*TO PRESERVE THRESHOLD ACCURACY, SET PARALLEL COMBINATION OF R1 AND R2 $\leq 66.5\text{k}$

TYPICAL APPLICATIONS

Dual Supply Monitor (3.3V and 5V, Defeat V_{CCA} Input)


Dual Supply Monitor (3.3V or 5V Plus Adjustable)




*TO PRESERVE THRESHOLD ACCURACY, SET PARALLEL COMBINATION OF $R1$ AND $R2 \leq 66.5k$

REFER TO LTC1728-5 OVERRIDE FUNCTIONS IN THE APPLICATIONS INFORMATION SECTION

Dual Supply Monitor (3.3V Plus Adjustable)




*TO PRESERVE THRESHOLD ACCURACY, SET PARALLEL COMBINATION OF $R1$ AND $R2 \leq 66.5k$

Using V_{CCA} Tied to DC/DC Feedback Divider

PACKAGE DESCRIPTION

MS8 Package
8-Lead Plastic MSOP

(Reference LTC DWG # 05-08-1660 Rev G)




NOTE:

1. DIMENSIONS IN MILLIMETER/(INCH)
2. DRAWING NOT TO SCALE
3. DIMENSION DOES NOT INCLUDE MOLD FLASH, PROTRUSIONS OR GATE BURRS.
MOLD FLASH, PROTRUSIONS OR GATE BURRS SHALL NOT EXCEED 0.152mm (.006") PER SIDE
4. DIMENSION DOES NOT INCLUDE INTERLEAD FLASH OR PROTRUSIONS.
INTERLEAD FLASH OR PROTRUSIONS SHALL NOT EXCEED 0.152mm (.006") PER SIDE
5. LEAD COPLANARITY (BOTTOM OF LEADS AFTER FORMING) SHALL BE 0.102mm (.004") MAX


PACKAGE DESCRIPTION

S8 Package 8-Lead Plastic Small Outline (Narrow .150 Inch) (Reference LTC DWG # 05-08-1610 Rev G)



PACKAGE DESCRIPTION

S5 Package 5-Lead Plastic TSOT-23 (Reference LTC DWG # 05-08-1635)




S5 TSOT-23 0302

REVISION HISTORY (Revision history begins at Rev C)

REV	DATE	DESCRIPTION	PAGE NUMBER
C	01/16	Updated package drawings.	14-16
D	10/16	Corrected maximum temperature for E-grade.	2
E	05/19	Corrected orderable part number (LTC1727EMS8-2.5#PBF → LTC1727EMS8-5#PBF)	2

TYPICAL APPLICATION

Triple Supply Monitor with Manual Reset Button



RELATED PARTS

PART NUMBER	DESCRIPTION	COMMENTS
LTC690	5V Supply Monitor, Watchdog Timer and Battery Backup	4.65V Threshold
LTC694-3.3	3.3V Supply Monitor, Watchdog Timer and Battery Backup	2.9V Threshold
LTC699	5V Supply Monitor and Watchdog Timer	4.65V Threshold
LTC1232	5V Supply Monitor, Watchdog Timer and Push-Button Reset	4.37V/4.62V Threshold
LTC1326	Micropower Precision Triple Supply Monitor for 5V, 3.3V and ADJ	4.725V, 3.118V, 1V Thresholds (±0.75%)
LTC1326-2.5	Micropower Precision Triple Supply Monitor for 2.5V, 3.3V and ADJ	2.363V, 3.118V, 1V Thresholds (±0.75%)
LTC1443/LTC1444 LTC1445	Micropower Quad Comparators with 1% Reference	LTC1443 Has 1.182V Reference, LTC1444/LTC1445 Have 1.221V Reference and Adjustable Hysteresis
LTC1536	Precision Triple Supply Monitor for PCI Applications	Meets PCI t_{FAIL} Timing Specifications
LTC1540	Nanopower Comparator with 2% Reference	1.182V Reference, 300nA Supply Current, 8-Pin MSOP
LTC1726-2.5	Micropower Triple Supply Monitor for 2.5V, 3.3V and ADJ	Adjustable $\overline{RESET}$ and Watchdog Time Outs
LTC1726-5	Micropower Triple Supply Monitor for 5V, 3.3V and ADJ	Adjustable $\overline{RESET}$ and Watchdog Time Outs
LTC1985-1.8	Micropower Triple Supply Monitor for 3.3V, 1.8V and ADJ	Push-Pull $\overline{RESET}$ Output, SOT-23