# **NDY Series**

### Isolated 3W Wide Input DC-DC Converters

OUTPUT CHARACTERISTICS						
Parameter	Conditions	Min.	Тур.	Max.	Units	
Voltage set point accuracy	With external input/output capacitors		±1	±5	%	
Line regulation	Low line to high line, 3.3V output with external input/output capacitors		0.05	0.25	%	
	Low line to high line, all other outputs with external input/output capacitors		0.05	0.5	%	
Load regulation	25% load to 100% load, 3.3V output with external input/output capacitors		0.6	1.0	%	
	25% load to 100% load, all other outputs with external input/output capacitors		0.2	0.5	%	
Ripple <sup>1</sup>	BW = 20Hz to 300kHz, 3.3V output with external input/output capacitors		80	120	mV rms	
	BW = 20Hz to 300kHz, all other outputs with external input/output capacitors		5	10		
Noise <sup>1</sup>	BW = DC to 100MHz, 3.3V output with external input/output capacitors			180	m\/ n n	
	BW=DC to 20MHz, all other outputs with external input/output capacitors		50	100	IIIv h-h	

ISOLATION CHARACTERISTICS						
Parameter	Conditions	Min.	Тур.	Max.	Units	
Isolation test voltage	Flash tested for 1 second	1000			VDC	
Resistance	Viso=500VDC	1			GΩ	

GENERAL CHARACTERISTICS						
Parameter	Conditions	Min.	Тур.	Max.	Units	
Switching frequency	100% load V <sub>IN</sub> nominal 3.3V output	160		220	kHz	
	25% load VIN nominal 3.3V output	290		560		
	100% load V <sub>IN</sub> nominal, all other outputs	80		220		
	25% load V <sub>IN</sub> nominal, all other outputs	290		560		

TEMPERATURE CHARACTERISTICS					
Parameter	Conditions	Min.	Тур.	Max.	Units
Operation	Ambient temperature	-40		85	00
Storage		-50		130	-0
Cooling	Free air convection				

ABSOLUTE MAXIMUM RATINGS	
Short-circuit protection	Continuous
Lead temperature 1.5mm from case for 10 seconds	260°C
Minimum load	25% of rated load
Wave Solder	Wave Solder profile not to exceed the profile recommended in IEC 61760-1 Section 6.1.3. Please refer to <u>application notes</u> for further information.
Input voltage 05 types	10V
Input voltage 12 types	20V
Input voltage 24 types	40V
Input voltage 48 types	80V
Internal dissipation	1.7W

1. For lower ripple refer to circuit for reduced ripple.

# **NDY Series**

### Isolated 3W Wide Input DC-DC Converters

### **TECHNICAL NOTES**

### **ISOLATION VOLTAGE**

'Hi Pot Test', 'Flash Tested', 'Withstand Voltage', 'Proof Voltage', 'Dielectric Withstand Voltage' & 'Isolation Test Voltage' are all terms that relate to the same thing, a test voltage, applied for a specified time, across a component designed to provide electrical isolation, to verify the integrity of that isolation.

Murata Power Solutions NDY series of DC-DC converters are all 100% production tested at their stated isolation voltage. This is 1kVDC for 1 second.

A question commonly asked is, "What is the continuous voltage that can be applied across the part in normal operation?"

The NDY series has been recognised by Underwriters Laboratory for functional isolation. Both input and output should normally be maintained within SELV limits i.e. less than 42.4V peak, or 60VDC. The isolation test voltage represents a measure of immunity to transient voltages and the part should never be used as an element of a safety isolation system. The part could be expected to function correctly with several hundred volts offset applied continuously across the isolation barrier; but then the circuitry on both sides of the barrier must be regarded as operating at an unsafe voltage and further isolation/insulation systems must form a barrier between these circuits and any user-accessible circuitry according to safety standard requirements.

#### **REPEATED HIGH-VOLTAGE ISOLATION TESTING**

It is well known that repeated high-voltage isolation testing of a barrier component can actually degrade isolation capability, to a lesser or greater degree depending on materials, construction and environment. The NDY series has an El ferrite core, with no additional insulation between primary and secondary windings of enamelled wire. While parts can be expected to withstand several times the stated test voltage, the isolation capability does depend on the wire insulation. Any material, including this enamel (typically polyurethane) is susceptible to eventual chemical degradation when subject to very high applied voltages thus implying that the number of tests should be strictly limited. We therefore strongly advise against repeated high voltage isolation testing, but if it is absolutely required, that the voltage be reduced by 20% from specified test voltage.

This consideration equally applies to agency recognised parts rated for better than functional isolation where the wire enamel insulation is always supplemented by a further insulation system of physical spacing or barriers.

#### SAFETY APPROVAL

The NDY series has been recognised by Underwriters Laboratory (UL) to UL 60950 for functional insulation for a maximum case temperature limit of 130°C (case temperature measured on the face opposite the pins). File number E151252 applies.

Note: This series gained UL 60950 recognition for products manufactured on or after date code G1123, any NDY parts manufactured before this date code should not be considered UL 60950 recognised. Any NDY that is UL recognised will be printed with the UL logo.

#### **RoHS COMPLIANCE INFORMATION**



This series is compatible with RoHS soldering systems with a peak wave solder temperature of 260°C for 10 seconds. Please refer to <u>application</u> <u>notes</u> for further information. The pin termination finish on this product series is Bright Tin. The series is backward compatible with Sn/Pb soldering systems.

For further information, please visit www.murata-ps.com/rohs

### PART NUMBER STRUCTURE

Series name		RoHS compliant
Input voltage		Output voltage

www.murata.com

# **NDY Series**

Isolated 3W Wide Input DC-DC Converters

### APPLICATION NOTES Recommended input & output capacitors Although these converters will work without external capacitors, they are necessary in order to guarantee the full parametric performance over the full line and load range. All parts have been tested and characterised using the following values and test circuit. Input Voltage Cin Output Voltage Соит Lout 100µF, 25V (0.25Ω at 100KHz) MPS# - 24100C 5V, 12V 3.3V 100μF, 25V (0.25Ω at 100KHz) 10µF, 100V (1.5Ω at 100KHz) 5V, 12V, 15V 24V, 48V Not required Test circuit, 5V, 12V and 15V output + V<sub>IN</sub> o-----\_\_\_\_\_\_\_\_\_ + V\_\_\_\_\_ = Cin NDY COUT \_\_\_ - V<sub>out</sub> - V<sub>IN</sub> o-----Recommended circuit for reduced ripple 3.3V output L<sub>OUT</sub> + V<sub>IN</sub> 0------= Cin **NDY** Соит \_\_\_\_ - V\_\_\_\_\_ - V<sub>IN</sub> o------Output load

The minimum rated load across the whole input voltage range is 25% of the full load output. It is important to take care that the load does not fall below this as the output ripple will greatly increase. While this condition will not harm the device the resultant increase in output ripple could cause customer's application to malfunction.

### NDY05 POWER DERATING CURVE



# **NDY Series**

Isolated 3W Wide Input DC-DC Converters



Downloaded from Arrow.com.

## ed 3W Wide Input DC-DC Converters

**NDY Series** 

### Isolated 3W Wide Input DC-DC Converters

#### DISCLAIMER

Unless otherwise stated in the datasheet, all products are designed for standard commercial and industrial applications and NOT for safety-critical and/or life-critical applications.

Particularly for safety-critical and/or life-critical applications, i.e. applications that may directly endanger or cause the loss of life, inflict bodily harm and/or loss or severe damage to equipment/property, and severely harm the environment, a prior explicit written approval from Murata is strictly required. Any use of Murata standard products for any safety-critical, life-critical or any related applications without any prior explicit written approval from Murata shall be deemed unauthorised use.

These applications include but are not limited to:

- Aircraft equipment
- Aerospace equipment
- Undersea equipment
- Power plant control equipment
- Medical equipment
- Transportation equipment ( automobiles, trains, ships, etc.)
- Traffic signal equipment
- Disaster prevention / crime prevention equipment
- Data Processing equipment

Murata makes no express or implied warranty, representation, or guarantee of suitability, fitness for any particular use/purpose and/or compatibility with any application or device of the buyer, nor does Murata assume any liability whatsoever arising out of unauthorised use of any Murata product for the application of the buyer. The suitability, fitness for any particular use/purpose and/or compatibility of Murata product with any application or device of the buyer remain to be the responsibility and liability of the buyer.

Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards that anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm, and take appropriate remedial actions. Buyer will fully indemnify and hold Murata, its affiliated companies, and its representatives harmless against any damages arising out of unauthorised use of any Murata products in any safety-critical and/ or life-critical applications.

Remark: Murata in this section refers to Murata Manufacturing Company and its affiliated companies worldwide including, but not limited to, Murata Power Solutions.



This product is subject to the following <u>operating requirements</u> and the <u>Life and Safety Critical Application Sales Policy</u>: Refer to: https://www.murata.com/en-eu/products/power/requirements

Murata Power Solutions (Milton Keynes) Ltd. makes no representation that the use of its products in the circuits described herein, or the use of other technical information contained herein, will not infringe upon existing or future patent rights. The described herein do not imply the granting of licenses to make, use, or sell equipment constructed in accordance therewith. Specifications are subject to change without notice.

www.murata.com

KDC\_NDY.LO1 Page 6 of 6