

Fig. 3 Typical Total Capacitance vs. Nominal Zener Voltage


Ordering Information (Note 7)

Part Number	Case	Packaging	
(Type Number)-7-F*	SOT-23	3000/Tape & Reel	

^{*}Add "-7" to the appropriate type number in Electrical Characteristics Table on Page 2. Example: 43V Zener = BZX84C43-7-F.

7. For packaging details, go to our website at http://www.diodes.com/datasheets/ap02007.pdf.

Marking Information



Kxx = Product Type Marking Code (See Electrical Characteristics Table) YM = Date Code Marking Y = Year ex: T = 2006




xx = Product Type Marking Code (See Electrical Characteristics Table) YM = Date Code Marking Y = Year ex: T = 2006 M = Month (ex: 9 = September)

Date Code Key

Year	2006	2007	20	80	2009	2010	2011	2012	2 20	13	2014	2015
Code	Т	U	'	/	W	Χ	Υ	Z	,	4	В	С
Month	Jan	Feb	Mar	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec
Code	1	2	3	4	5	6	7	8	9	0	N	D




Package Outline Dimensions



SOT-23				
Dim	Min	Max		
Α	0.37	0.51		
В	1.20	1.40		
С	2.30	2.50		
D	0.89	1.03		
F	0.45	0.60		
G	1.78	2.05		
Н	2.80	3.00		
J	0.013	0.10		
K	0.903	1.10		
L	0.45	0.61		
M	0.085	0.180		
α	0°	8°		

Suggested Pad Layout



Dimensions	Value (in mm)
Z	2.9
Х	0.8
Y	0.9
С	2.0
Е	1.35

IMPORTANT NOTICE

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to any product herein. Diodes Incorporated does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

LIFE SUPPORT

Diodes Incorporated products are not authorized for use as critical components in life support devices or systems without the expressed written approval of the President of Diodes Incorporated.