

Selection Guide

Part Number	Packing*	Package
A3910EEETR-T	3000 pieces per 7-in. reel	8-contact DFN with exposed thermal pad

*Contact Allegro™ for additional packing options.

Absolute Maximum Ratings*

Characteristic	Symbol	Notes	Rating	Unit
Supply Voltage	V_{BB}		-0.3 to 5.5	V
Logic Input Voltage Range	V_{IN}		-0.3 to 6	V
Output Current	I_{OUT}		500	mA
Output Voltage	V_{OUT}		-0.3 to $V_{BB} + 1$	V
Operating Ambient Temperature	T_A	E temperature range	-40 to 85	°C
Maximum Junction Temperature	$T_{J(max)}$		150	°C
Storage Temperature	T_{stg}		-55 to 150	°C

Thermal Characteristics may require derating at maximum conditions, see application information


Characteristic	Symbol	Test Conditions*	Value	Unit
Package Thermal Resistance	$R_{\theta JA}$	On 4-layer PCB based on JEDEC standard	49	°C/W
		On 2-layer PCB based with 0.23 in. ² exposed copper each side	92	°C/W

*Additional thermal information available on the Allegro website.

Terminal List Table

Number	Name	Function
1	HIN1	Logic input
2	LIN1	Logic input
3	LIN2	Logic input
4	HIN2	Logic input
5	OUT2	Motor terminal
6	GND	Ground
7	VBB	Input Supply
8	OUT1	Motor terminal

Pin-out Diagram



ELECTRICAL CHARACTERISTICS* Valid at $T_A = 25^\circ\text{C}$; unless otherwise specified

Characteristic	Symbol	Test Conditions	Min.	Typ.	Max.	Unit
VBB Supply Range	V_{BB}		2.5	–	5.5	V
VBB Supply Current	I_{BB}	Both bridges, PWM = 50 kHz	–	0.3	1	mA
		Sleep mode ($HIN1=HIN2=LIN1=LIN2=0V$)	–	<1	1	μA
Output Driver On-Resistance	$R_{DS(on)}$	Source driver, $I = 400\text{ mA}$, $V_{BB} = 3\text{ V}$	–	1.1	1.4	Ω
		Source driver, $I = 400\text{ mA}$, $V_{BB} = 5\text{ V}$	–	0.8	1	Ω
		Sink driver, $I = 400\text{ mA}$, $V_{BB} = 3\text{ V}$	–	0.5	0.65	Ω
		Sink driver, $I = 400\text{ mA}$, $V_{BB} = 5\text{ V}$	–	0.4	0.52	Ω
Input Logic Low Level	V_{IL}		–	–	0.5	V
Input Logic High Level	V_{IH}		$V_{BB}/2$	–	–	V
Input Hysteresis	V_{HYS}		50	150	300	mV
Logic Input Current	I_{IN}	$V_{IN} = 3.3\text{ V}$ (Pulldown = 100 k Ω)	–	33	50	μA
Thermal Shutdown Temperature	T_{JTSD}	Temperature increasing	–	165	–	$^\circ\text{C}$
Thermal Shutdown Hysteresis	ΔT_J	Recovery = $T_{JTSD} - \Delta T_J$	–	15	–	$^\circ\text{C}$

*Specified limits are tested at a single temperature and assured over operating temperature range by design and characterization.

Logic Table


HINx	LINx	OUTx	Function Motor to Supply	Function Motor to GND
0	0	Hi-Z ¹	Coast (Sleep ²)	Coast (Sleep ²)
1	0	High	Brake	Drive
0	1	Low	Drive	Brake
1	1	Hi-Z ¹	Coast	Coast

¹Hi-Z is high impedance.


²Sleep mode activated by all four inputs <100 mV.

Characteristic Performance

Output On-Resistance versus Load Supply Voltage



Output On-Resistance versus Output Current




Package EE, 8-Contact DFN with Exposed Thermal Pad

For Reference Only – Not for Tooling Use

(Reference DWG-0000369)

NOT TO SCALE

All dimensions nominal unless otherwise stated – Dimensions in millimeters
Exact case and lead configuration at supplier discretion within limits shown



Revision History

Number	Date	Description
1	July 23, 2013	Update Selection Guide
2	April 10, 2019	Minor editorial updates
3	April 30, 2021	Updated Package Outline Drawing (page 6)

Copyright 2021, Allegro MicroSystems.

Allegro MicroSystems reserves the right to make, from time to time, such departures from the detail specifications as may be required to permit improvements in the performance, reliability, or manufacturability of its products. Before placing an order, the user is cautioned to verify that the information being relied upon is current.

Allegro's products are not to be used in any devices or systems, including but not limited to life support devices or systems, in which a failure of Allegro's product can reasonably be expected to cause bodily harm.

The information included herein is believed to be accurate and reliable. However, Allegro MicroSystems assumes no responsibility for its use; nor for any infringement of patents or other rights of third parties which may result from its use.

Copies of this document are considered uncontrolled documents.

For the latest version of this document, visit our website:

www.allegromicro.com