APPLICATIONS

- Power supply for electronic control units such as EV inverter and battery charge control unit.

SELECTION GUIDE

The package type, the set output voltage and the auto-discharge(1) are user-selectable options.

Selection Guide

Product Name	Package	Quantity per Reel	Pb Free	Halogen Free
RP115Lxx2∗(y)-TR-#	DFN2020-8B	3,000 pcs	Yes	Yes
RP115Hxx1∗(y)-T1-#E	SOT-89-5	1,000 pcs	Yes	Yes

xx: Set Output Voltage (V_{SET})

0.9 V (09) / 1.0 V (10) / 1.1 V (11) /1.2 V (12) / 1.5 V (15) / 1.8 V (18) / 2.5 V (25) / 2.8 V (28) / 3.0 V (30) / 3.3 V (33) / 3.4 V (34) / 3.9 V (39)

Note: Contact Ricoh sales representatives for other voltages.

xx, (y): Second Decimal Place of 1.25 V RP115x12x∗5-TR-A

Second Decimal Place of 1.75 V RP115L172∗5-TR-A

∗: Auto-discharge Option

(B) auto-discharge not included

(D) auto-discharge included

#: Quality Class

	Operating Temp. Range	Test Temp.
A	−40°C to 105°C	25°C, High

(1) Auto-discharge function quickly lowers the output voltage to 0 V by releasing the electrical charge in the external capacitor when the chip enable signal is switched from the active mode to the standby mode.

Downloaded from Arrow.com.

BLOCK DIAGRAMS



RP115Lxx2B Block Diagram



RP115Lxx2D Block Diagram



RP115Hxx1B[(1)] Block Diagram



RP115Hxx1D[(1)] Block Diagram

(1) The RP115H does not have the LCON pin, so the output current is fixed at 1 A.

Downloaded from Arrow.com.

PIN DESCRIPTION



DFN2020-8B Pin Configuration **SOT-89-5 Pin Configuration**

RP115L: DFN2020-8B

Pin No	Symbol	Pin Description
1	VOUT(1)	Output Pin
2	VOUT (1)	Output Pin
3	LCON	Output Current Limit Alternate Pin (“H” = 1 A, “L” = 500 mA)
4	VFB (1)	Feedback Pin
5	GND	Ground Pin
6	CE	Chip Enable Pin
7	VDD(2)	Input Pin
8	VDD (2)	Input Pin

∗ The tab on the bottom of the package shown by blue circle is a substrate potential (GND). It is recommended that this tab be connected to the ground plane pin on the board but it is possible to leave the tab floating.

RP115H(3): SOT-89-5

Pin No	Symbol	Pin Description
1	VFB (1)	Feedback Pin
2	GND	Ground Pin
3	CE	Chip Enable Pin
4	VDD	Input Pin
5	VOUT (1)	Output Pin

(1) The VOUT and the VFB pins must be wired together when mounting on the board.
(2) The VDD pin must be wired together when mounting on the board.
(3) Output Current Limit is fixed at 1 A.

Downloaded from Arrow.com.

ABSOLUTE MAXIMUM RATINGS

Absolute Maximum Ratings

Symbol	Parameter		Rating		Unit
V_{IN}	Input Voltage		6.0		V
V_{CE}	CE Pin Input Voltage		−0.3 to 6.0		V
V_{LCON}	LCON Pin Input Voltage		−0.3 to 6.0		V
V_{OUT}	Output Voltage		−0.3 to 6.0		V
P_D	Power Dissipation(1)	JEDEC STD. 51-7	DFN2020-8B	2800	mW
		JEDEC STD. 51-7	SOT-89-5	3200	
Tj	Junction Temperature Range		−40 to 150		ºC
Tstg	Storage Temperature Range		−55 to 150		ºC

ABSOLUTE MAXIMUM RATINGS

Electronic and mechanical stress momentarily exceeded absolute maximum ratings may cause permanent damage and may degrade the life time and safety for both device and system using the device in the field.
The functional operation at or over these absolute maximum ratings are not assured.

RECOMMENDED OPERATING CONDITIONS

Recommend Operating Conditions

Symbol	Parameter	Rating	Unit
V_{IN}	Input Voltage(2)	1.4 to 5.25	V
Ta	Operating Temperature Range	−40 to 105	ºC

RECOMMENDED OPERATING CONDITONS

All of electronic equipment should be designed that the mounted semiconductor devices operate within the recommended operating conditions. The semiconductor devices cannot operate normally over the recommended operating conditions, even if they are used over such ratings by momentary electronic noise or surge. And the semiconductor devices may receive serious damage when they continue to operate over the recommended operating conditions.

(1) Refer to *POWER DISSIPATION* for detailed information.
(2) The maximum input voltage listed under *Electrical Characteristics* is 5.25 V. If for any reason the input voltage exceeds 5.25 V, it has to be no more than 5.5 V with 500 cumulative operating hours.

Downloaded from Arrow.com.

ELECTRICAL CHARACTERISTICS

V_{IN} = V_{SET}[1] + 1.0 V, I_{OUT} = 1 mA, C_{IN} = C_{OUT} = 1.0 µF, unless otherwise noted.

The specifications in [ ] are guaranteed by design engineering at −40°C ≤ Ta ≤ 105°C.

RP115x (-AE) Electrical Characteristics (Ta = 25°C)

Symbol	Parameter	Test Conditions/Comments		Min.	Typ.	Max.	Unit
V_{OUT}	Output Voltage	Ta = 25°C	V_{SET} ≥ 1.75 V	x0.99		x1.01	V
			V_{SET} < 1.75 V	-18		+18	mV
		−40°C ≤ Ta ≤ 105°C	V_{SET} ≥ 1.75 V	[x0.981]		[x1.015]	V
			V_{SET} < 1.75 V	Refer to *Output Voltage*			
I_{LIM}	Output Current Limit	V_{IN} = V_{SET} + 0.5 V	LCON = "L"	[500]			mA
			LCON = "H"[2]	[1.0]			A
ΔV_{OUT} /ΔI_{OUT}	Load Regulation	V_{IN} = V_{SET} + 0.5 V 1 mA ≤ I_{OUT} ≤ 500 mA	LCON = "L"		1	[20]	mV
		V_{IN} = V_{SET} + 0.5 V 1mA ≤ I_{OUT} ≤ 1.0 A	LCON = "H"[2]			[40]	
V_{DIF}	Dropout Voltage	Refer to *Dropout Voltage*					
I_{SS}	Supply Current	I_{OUT} = 0 mA			110	[160]	µA
Istandby	Standby Current	V_{CE} = 0 V			0.5	[30]	µA
ΔV_{OUT} /ΔV_{IN}	Line Regulation	V_{SET} + 0.5 V ≤ V_{IN} ≤ 5.25 V (V_{IN} ≥ 1.4 V)			0.02	[0.10]	%/V
I_{SC}	Short Current Limit	V_{OUT} = 0 V [3]	LCON = "L"		60	[95]	mA
			LCON = "H" [2]		110	[155]	
I_{CE}	CE Pull-down Current			[0.05]	0.3	[0.6]	µA
V_{CEH}	CE Input Voltage "H"			[1.0]			V
V_{CEL}	CE Input Voltage "L"					[0.4]	V
I_{LCON}	LCON Pull-down Current (RP115L only)			[0.05]	0.3	[0.6]	µA
V_{LCONH}	LCON Input Voltage "High" (RP115L only)			[1.0]			V
V_{LCONL}	LCON Input Voltage "Low" (RP115L only)					[0.4]	V

[1] V_{SET} = Set Output Voltage

[2] RP115H: Same Electrical Characteristics as LCON = "H".

[3] Short Current is the value when V_{OUT} and GND are short-circuited after the device starts up. Inrush Current flows when the device starts up while V_{OUT} and GND are short-circuited.

Downloaded from Arrow.com.

ELECTRICAL CHARACTERISTICS (continued)

V_{IN} = V_{SET}[1] + 1.0 V, I_{OUT} = 1 mA, C_{IN} = C_{OUT} = 1.0 µF, unless otherwise noted.

The specifications in [ ] are guaranteed by design engineering at −40°C ≤ Ta ≤ 105°C.

RP115x (-AE) Electrical Characteristics (Ta = 25°C)

Symbol	Parameter	Test Conditions/Comments		Min.	Typ.	Max.	Unit
T_{TSD}	Thermal Shutdown Threshold Temeprature	Tj, Rising			165		°C
T_{TSR}	Thermal Shutdown Threshold Temperature	Tj, Falling			110		°C
I_{REV}	Reverse Current	V_{OUT} = V_{SET} + 1.0 V 0 ≤ V_{IN} ≤ V_{OUT}	V_{SET} ≥ 1.75 V		7.5		µA
			V_{SET} < 1.75 V		10		
V_{REV_DET} [2]	Detection Offset in Reverse Current Mode[3]	V_{OUT} ≥ 0.7 V, 0 ≤ V_{IN} ≤ 5.25 V			20		mV
V_{REV_REL} [4]	Release Offset in Reverse Current Mode [3]	V_{OUT} ≥ 0.7 V, 0 ≤ V_{IN} ≤ 5.25 V			30	[50]	mV
R_{LOW}	Low-output Nch Tr. ON Resistance (RP115xxxD only)	V_{IN} = 4.0 V, V_{CE} = 0 V			60		Ω
I_{RUSH}	Inrush limited Current	CC mode[5]	LCON = ”L”		300		mA
			LCON = ”H” [6]		500		

All test items listed under Electrical Characteristics are done under the pulse load condition (Tj ≈ Ta = 25ºC) except Output Noise, Ripple Rejection, and Output Voltage Temperature Coefficient.

[1] V_{SET} = Set Output Voltage

[2] V_{REV_DET} = V_{IN} − V_{OUT}

[3] Guaranteed operating range of reverse current protection circuit is V_{OUT} ≥ 0.7 V. When V_{IN} = V_{OUT} = 0 V, reverse current protection mode is constantly active.

[4] V_{REV_REL} = V_{IN} − V_{OUT}

[5] For CC (Constant Current) Mode, please refer to *Start-up Characteristics*.

[6] RP115H: Same Electrical Characteristics as LCON = ”High”.

Downloaded from Arrow.com.

Output Voltage

Product Name	Output Voltage V_{OUT} (V)		
	Min.	Typ.	Max.
RP115x09x	0.862	0.9	0.930
RP115x10x	0.960	1.0	1.031
RP115x11x	1.058	1.1	1.133
RP115x12x	1.156	1.2	1.234
RP115x12x5	1.205	1.25	1.285
RP115x15x	1.449	1.5	1.538

Dropout Voltage **(Ta = 25ºC)**

Set Output Voltage V_{SET} (V)	Dropout Voltage V_{DIF} (V)					
	RP115L				RP115H	
	I_{OUT} = 500 mA		I_{OUT} = 1000 mA		I_{OUT} = 1000 mA	
	Typ.	Max.	Typ.	Max.	Typ.	Max.
0.9 V, 1.0 V	*	*	*	*	*	*
1.1 V	*	*	*	0.375	*	0.365
1.2 V, 1.25 V	*	*	0.195	0.355	0.235	0.345
1.5 V	0.085	0.170	0.165	0.320	0.205	0.310
1.75 V, 1.8 V, 2.5 V	0.075	0.160	0.150	0.295	0.190	0.285
2.8 V, 3.0 V	0.065	0.145	0.130	0.265	0.170	0.255
3.3 V, 3.4 V, 3.9 V	0.060	0.135	0.125	0.250	0.165	0.240

If the dropout voltage falls below the release offset value of reverse current protection mode (V_{REV_REL}), the reverse current protection circuit may repeat the detection and release operations. Please refer to *Reverse Current Protection*.

* Input voltage should be equal or more than the minimum operating voltage (1.4 V).

Downloaded from Arrow.com.

THEORY OF OPERATION

Reverse Current Protection

The RP115x includes a reverse current protection circuit in order to stop the reverse current from VOUT pin to V_{DD} pin or to GND pin when V_{OUT} becomes higher than V_{IN}.

Usually, the LDO using Pch output transistor contains a parasitic diode between VDD pin and VOUT pin.

Therefore, if V_{OUT} is higher than V_{IN}, the parasitic diode becomes forward direction. As a result, the current flows from VOUT pin to VDD pin.

The RP115x switches the mode to the reverse current protection mode before V_{IN} becomes lower than V_{OUT} by connecting the parasitic diode of Pch output transistor to the backward direction, and connecting the gate to VOUT pin. As a result, the Pch output transistor is turned off. However, from VOUT pin to GND pin, via the internal divider resistors, very small current I_{REV} flows.

Switching to either the normal mode or to the reverse current protection mode is determined by the magnitude of V_{IN} voltage and V_{OUT} voltage. For the stable operation, offset and hysteresis are set as the threshold. The detector threshold is set to V_{REV_DET} and the released voltage is set to V_{REV_REL}. Therefore, the minimum dropout voltage under the small load current condition is restricted by the value of V_{REV_REL}.

Following figures show the diagrams of each mode, and the load characteristics of each mode. When giving the VOUT pin a constant-voltage and decreasing V_{IN}, the dropout voltage will become lower than V_{REV_DET}. As a result, the reverse current protection starts to function to stop the load current.

By increasing the dropout voltage higher than V_{REV_REL}, the protection mode will be released to let the load current to flow. If the dropout voltage to be used is lower than V_{REV_REL}, the detection and the release may be repeated.

The operating voltage guaranteed level of the reverse current protection circuit is for $V_{OUT} \geq 0.7$ V. If $V_{IN} = 0$ V, the reverse current protection mode becomes always active.



Normal Operation Mode



Reverse Current Protection Mode

Downloaded from Arrow.com.



Detection/ Release Timing of Reverse Current Protection Function

Constant Slope for Start-Up Characteristics

The RP115x includes a constant slope circuit in order to prevent the overshoot of the output voltage. The start-up time (t_{ON}) is 100 µs (Typ.). If inrush current increases due to the large capacitance of C_{OUT}, the operation mode will be shifted from Constant Slope (CS) mode to Constant Current (CC) mode. The CC mode maintains a constant level of inrush current. In the CC mode, t_{ON} varies according to the size of C_{OUT} and the amount of load current.

Start-up Time and Inrush Current Estimations

Start-up time and inrush current in the CS mode and the CC mode can be estimated as follows. The following is described the how to estimate when using the RP115L. The RP115H has the same electrical characteristics as LCON = "H" in the RP115L.

[CS Mode]

Start-up Time (t_{ON}): 100 µs (Typ.)

Inrush Current (I_{RUSH}): $C_{OUT} \cdot V_{SET} / t_{ON} + I_{OUT}$ (1)

Note: If the result of the above calculation is more than the following values, the operation mode will be shifted from the CS mode to the CC mode.

LCON = "L" ····· 300 mA (Typ.)

LCON = "H" ····· 500 mA (Typ.)

[CC Mode]

Start-up Time (t_{ON}): $C_{OUT} \cdot V_{SET} / I_{CO}$ (2)

Inrush Current (I_{RUSH}): LCON = "L" ····· 300 mA (Typ.)

LCON = "H" ····· 500 mA (Typ.)

(1) I_{OUT}: When R_{LOAD} is connected to load, I_{OUT} can be calculated by $R_{LOAD} = V_{SET} / I_{OUT}$.

(2) I_{CO}: I_{CO} is a charge current of C_{OUT} and can be calculated roughly by $I_{RUSH} \approx I_{CO} + I_{OUT}$.

Downloaded from Arrow.com.



Circuit Example of RP115L



Start-up Operation Diagram

Downloaded from Arrow.com.

Precautions before Use

During the start-up, the inrush current limit circuit is in operation; therefore, the load current (I_{OUT}) should be drawn after the output voltage (V_{OUT}) reached the preset value (Best timing: t_{ON} + 60µs or more). If the load current is drawn during the start-up, it should be within the following values.

LCON = ”L” ····· $I_{OUT} \leq 150$ mA
LCON = ”H” ····· $I_{OUT} \leq 350$ mA

In the CC mode, I_{RUSH} is limited until V_{OUT} reaches the preset value. $I_{RUSH} \approx I_{CO} + I_{OUT}$ is true; therefore, if large I_{OUT} is drawn during the start-up, the charge current (I_{CO}) of C_{OUT} decreases and t_{ON} becomes longer. Please refer to *Start-up Time and Inrush Current Estimations*.

In order to control the start-up operation by using the CS mode or CC mode, input “H” into the CE pin while $V_{IN} \geq 1.4$ V. If “H” is input into the CE pin while V_{IN} is less than the minimum operating voltage, the operation may not be controlled by the CS mode or CC mode.

When starting up the device while the short circuit is occurring between the V_{OUT} pin and GND, the short current protection circuit does not control the current but the current limit circuit does.
When there’s excessive heat generation in the device, thermal shutdown circuit shuts down the circuitry before the device overheats dangerously.

LCON Pin Operation (RP115L Only)

By alternating the LCON pin between “H” or “L”, the RP115L can choose the output current limit either 1.0 A or 500 mA. Please note that during start-up (t_{ON} + 60 µs (Typ.)), do not change the logic of the LCON pin.

LCON = ”L” ····· 500 mA
LCON = ”H” ····· 1.0 A

Application Example

Even when using the RP115L with LCON = ”H”, I_{RUSH} in the CC mode can be reduced from 500 mA (Typ.) to 300 mA (Typ.) by starting up the IC with LCON = ”L”. Please refer to *Start-Up Characteristics*.

Downloaded from Arrow.com.

APPLICATION INFORMATION



RP115x Typical Application Circuit

External Components Example:

Symbol	Descriptions
C_{IN}	1.0 µF, Ceramic Capacitor, CGA3E1X7R1C105K080AC (TDK)
C_{OUT}	1.0 µF, Ceramic Capacitor, CGA3E1X7R1C105K080AC (TDK) 2.2 µF, Ceramic Capacitor, CGA4J3X7R1C225K125AB (TDK)

Precautions When Selecting External Components

- Connect a capacitor of 1.0 µF or more as C_{OUT} to secure stable operation even when the load current is varied. (for phase compensation)
- Depending on the capacitor size, manufacturer, and part number, the bias characteristics and temperature characteristics are different. Evaluate the circuit taking actual characteristics into account. Especially for the 1.75-V-output product, it is recommended to use 2.2 µF or higher output capacitor when the product is used under the low-temperature environment such as −20°C or lower.
- If using a tantalum type capacitor and the ESR value of the capacitor is large, the output might be unstable. Evaluate your circuit including consideration of frequency characteristics.

(3) The LCON pin is only included in RP115L (DFN2020-8B).
(4) The VOUT pin and the VFB pin should be wired together when mounting on the board.

Downloaded from Arrow.com.

Equivalent Series Resistance (ESR) vs. Output Current

Ceramic type output capacitor is recommended for the RP115x but any capacitor with low ESR can be used. The graphs below show the relation between I_{OUT} and ESR (noise level: average 40 μV or less).

Measurement Conditions

- Noise Frequency Band Width: 10 Hz to 2 MHz
- Operating Temperature Range: −40°C to +85°C
- Hatched Area: Output noise level is average 40 μV or less.
- C_{IN}, C_{OUT}: 1.0 μF or more





TECHNICAL NOTES

The performance of a power source circuit using this device is highly dependent on a peripheral circuit. A peripheral component or the device mounted on PCB should not exceed its rated voltage, rated current or rated power. When designing a peripheral circuit, please be fully aware of the following points.

- Ensure the V_{DD} and GND lines are sufficiently robust. If their impedance is too high, noise pickup or unstable operation may result. Connect a capacitor C_{IN} with 1.0 μF or more between VDD and GND pins, and as close as possible to the pins.
- Connect C_{OUT} capacitor with suitable values between the VOUT and GND pins, and as close as possible to the pins.

Downloaded from Arrow.com.

TYPICAL CHARACTERISTICS

Note: Typical Characteristics are intended to be used as reference data; they are not guaranteed.

1) Output Voltage vs. Input Voltage (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF, Ta = 25°C)

RP115x12xx



RP115x18xx



RP115x33xx



2) Supply Current vs. Input Voltage (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF, Ta = 25°C)

RP115x12xx



RP115x18xx



Downloaded from Arrow.com.



Note: The RP115x contains a peak current limit circuit which protect the regulator from damage by overcurrent if the output pin (VOUT) and the ground pin (GND) are shorted. The short-circuiting causes the overheating of the device which leads a thermal shutdown circuit to operate. If the peak current limit circuit and the thermal shutdown circuit work at the same time, fold-back type dropping characteristics cannot be measured. As for the short-circuit current and the peak current limit circuit, please refer to 3) Short Current Limit vs. Ambient Temperature and 4) Peak Current Limit vs. Ambient Temperature.

3) Short Current Limit vs. Ambient Temperature (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF)





4) Peak Current Limit vs. Ambient Temperature (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF)





Downloaded from Arrow.com.

5) Output Voltage vs. Ambient Temperature (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF, I_{OUT} = 1 mA)







6) Supply Current vs. Ambient Temperature (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF, I_{OUT} = 0 mA)





Downloaded from Arrow.com.



7) Dropout Voltage vs. Output Current (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF)







Downloaded from Arrow.com.

8) Dropout Voltage vs. Set Output Voltage (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF, Ta = 25°C)



9) Dropout Voltage vs. Ambient Temperature (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF)





Downloaded from Arrow.com.

10) Ripple Rejection vs. Input Voltage (C_{IN} = none, C_{OUT} = Ceramic 1.0 µF, Ripple = 0.2 Vp-p, Ta = 25°C)













Downloaded from Arrow.com.

11) Ripple Rejection vs. Frequency (C_{IN} = none or 0.47 µF, C_{OUT} = Ceramic 1.0 µF, Ripple = 0.2 Vp-p, Ta = 25°C)







12) Line Transient Response (C_{IN} = none, C_{OUT} = Ceramic 1.0 µF, I_{OUT} = 30 mA, tr = tf = 5 µs, Ta = 25°C)





Downloaded from Arrow.com.



13) Load Transient Response (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF, tr = tf = 0.5 µs, Ta = 25°C)









Downloaded from Arrow.com.

RP115x18xx



RP115x18xx



RP115x33xx



RP115x33xx



RP115x33xx



Downloaded from Arrow.com.

14) Turn-On Waveform Speed by CE Pin Signal (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF, Ta = 25°C)







15) Turn-Off Waveform Speed by CE Pin Signal (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF, Ta = 25°C)





Downloaded from Arrow.com.



16) Inrush Current at Turning-On (C_{IN} = Ceramic 1.0 µF, I_{OUT} = 0 mA, Ta = 25°C)









Downloaded from Arrow.com.





17) LCON Transient Response (C_{IN} = Ceramic 1.0 µF, C_{OUT} = Ceramic 1.0 µF, tr = tf = 0.5 µs, Ta = 25°C)









Downloaded from Arrow.com.





Downloaded from Arrow.com.

Ver. A

The power dissipation of the package is dependent on PCB material, layout, and environmental conditions. The following measurement conditions are based on JEDEC STD. 51-7.

Measurement Conditions

Item	Measurement Conditions
Environment	Mounting on Board (Wind Velocity = 0 m/s)
Board Material	Glass Cloth Epoxy Plastic (Four-Layer Board)
Board Dimensions	76.2 mm × 114.3 mm × 0.8 mm
Copper Ratio	Outer Layer (First Layer): Less than 95% of 50 mm Square Inner Layers (Second and Third Layers): Approx. 100% of 50 mm Square Outer Layer (Fourth Layer): Approx. 100% of 50 mm Square
Through-holes	ϕ 0.3 mm × 23 pcs

Measurement Result (Ta = 25°C, Tjmax = 150°C)

Item	Measurement Result
Power Dissipation	2800 mW
Thermal Resistance (θja)	θja = 44°C/W
Thermal Characterization Parameter (ψjt)	ψjt = 20°C/W

θja: Junction-to-Ambient Thermal Resistance

ψjt: Junction-to-Top Thermal Characterization Parameter



Power Dissipation vs. Ambient Temperature



Measurement Board Pattern

RICOH

Downloaded from Arrow.com.



DFN2020-8B Package Dimensions (Unit: mm)

∗ The tab on the bottom of the package is substrate level (GND). It is recommended that the tab be connected to the ground plane on the board, or otherwise be left floating.

Downloaded from Arrow.com.

Ver. A

The power dissipation of the package is dependent on PCB material, layout, and environmental conditions. The following measurement conditions are based on JEDEC STD. 51-7.

Measurement Conditions

Item	Measurement Conditions
Environment	Mounting on Board (Wind Velocity = 0 m/s)
Board Material	Glass Cloth Epoxy Plastic (Four-Layer Board)
Board Dimensions	76.2 mm × 114.3 mm × 0.8 mm
Copper Ratio	Outer Layer (First Layer): Less than 95% of 50 mm Square Inner Layers (Second and Third Layers): Approx. 100% of 50 mm Square Outer Layer (Fourth Layer): Approx. 100% of 50 mm Square
Through-holes	ϕ 0.3 mm × 13 pcs

Measurement Result (Ta = 25°C, Tjmax = 150°C)

Item	Measurement Result
Power Dissipation	3200 mW
Thermal Resistance (θja)	θja = 38°C/W
Thermal Characterization Parameter (ψjt)	ψjt = 13°C/W

θja: Junction-to-Ambient Thermal Resistance

ψjt: Junction-to-Top Thermal Characterization Parameter



Power Dissipation vs. Ambient Temperature



Measurement Board Pattern

Downloaded from Arrow.com.



SOT-89-5 Package Dimensions

Downloaded from Arrow.com.

1. The products and the product specifications described in this document are subject to change or discontinuation of production without notice for reasons such as improvement. Therefore, before deciding to use the products, please refer to Ricoh sales representatives for the latest information thereon.
2. The materials in this document may not be copied or otherwise reproduced in whole or in part without prior written consent of Ricoh.
3. Please be sure to take any necessary formalities under relevant laws or regulations before exporting or otherwise taking out of your country the products or the technical information described herein.
4. The technical information described in this document shows typical characteristics of and example application circuits for the products. The release of such information is not to be construed as a warranty of or a grant of license under Ricoh's or any third party's intellectual property rights or any other rights.
5. The products in this document are designed for automotive applications. However, when using the products for automotive applications, please make sure to contact Ricoh sales representative in advance due to confirming the quality level.
6. We are making our continuous effort to improve the quality and reliability of our products, but semiconductor products are likely to fail with certain probability. In order to prevent any injury to persons or damages to property resulting from such failure, customers should be careful enough to incorporate safety measures in their design, such as redundancy feature, fire containment feature and fail-safe feature. We do not assume any liability or responsibility for any loss or damage arising from misuse or inappropriate use of the products.
7. Anti-radiation design is not implemented in the products described in this document.
8. The X-ray exposure can influence functions and characteristics of the products. Confirm the product functions and characteristics in the evaluation stage.
9. WLCSP products should be used in light shielded environments. The light exposure can influence functions and characteristics of the products under operation or storage.
10. There can be variation in the marking when different AOI (Automated Optical Inspection) equipment is used. In the case of recognizing the marking characteristic with AOI, please contact Ricoh sales or our distributor before attempting to use AOI.
11. Please contact Ricoh sales representatives should you have any questions or comments concerning the products or the technical information.

RoHS Compliant
Halogen Free

Ricoh is committed to reducing the environmental loading materials in electrical devices with a view to contributing to the protection of human health and the environment.
Ricoh has been providing RoHS compliant products since April 1, 2006 and Halogen-free products since April 1, 2012.

RICOH RICOH ELECTRONIC DEVICES CO., LTD.

Official website
https://www.n-redc.co.jp/en/
Contact us
https://www.n-redc.co.jp/en/buy/

Downloaded from Arrow.com.