



# MCP73811/2

## Typical Applications



## Functional Block Diagram



## 1.0 ELECTRICAL CHARACTERISTICS

### Absolute Maximum Ratings†

V<sub>DDN</sub> ..... 7.0V  
 All Inputs and Outputs w.r.t. V<sub>SS</sub> ..... -0.3 to (V<sub>DD</sub>+0.3)V

Maximum Junction Temperature, T<sub>J</sub> ..... Internally Limited  
 Storage temperature ..... -65°C to +150°C  
 ESD protection on all pins  
 Human Body Model (1.5 kW in Series with 100 pF) ..... ≥ 4 kV  
 Machine Model (200pF, No Series Resistance) ..... 400V

† **Notice:** Stresses above those listed under “Maximum Ratings” may cause permanent damage to the device. This is a stress rating only and functional operation of the device at those or any other conditions above those indicated in the operational listings of this specification is not implied. Exposure to maximum rating conditions for extended periods may affect device reliability.

### DC CHARACTERISTICS

| Electrical Specifications: Unless otherwise indicated, all limits apply for V <sub>DD</sub> = [V <sub>REG</sub> (typ.) + 0.3V] to 6V, T <sub>A</sub> = -40°C to +85°C. Typical values are at +25°C, V <sub>DD</sub> = [V <sub>REG</sub> (typ.) + 1.0V] |                                                 |      |      |      |       |                                                                                  |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------|------|------|------|-------|----------------------------------------------------------------------------------|
| Parameters                                                                                                                                                                                                                                             | Sym                                             | Min  | Typ  | Max  | Units | Conditions                                                                       |
| Supply Input                                                                                                                                                                                                                                           |                                                 |      |      |      |       |                                                                                  |
| Supply Voltage                                                                                                                                                                                                                                         | V <sub>DD</sub>                                 | 3.75 | —    | 6    | V     |                                                                                  |
| Supply Current                                                                                                                                                                                                                                         | I <sub>SS</sub>                                 | —    | 1000 | 1500 | μA    | Charging                                                                         |
|                                                                                                                                                                                                                                                        |                                                 | —    | 50   | 100  | μA    | Standby (CE = V <sub>SS</sub> )                                                  |
|                                                                                                                                                                                                                                                        |                                                 | —    | 1.2  | 5    | μA    | Shutdown<br>(V <sub>DD</sub> ≤ V <sub>BAT</sub> - 100 mV)                        |
| Voltage Regulation (Constant Voltage Mode)                                                                                                                                                                                                             |                                                 |      |      |      |       |                                                                                  |
| Regulated Output Voltage                                                                                                                                                                                                                               | V <sub>REG</sub>                                | —    | 4.20 | —    | V     | V <sub>DD</sub> =[V <sub>REG</sub> (Typ)+1V]<br>I <sub>OUT</sub> =10 mA          |
| Output Voltage Tolerance                                                                                                                                                                                                                               | V <sub>RTOL</sub>                               | -1   | —    | +1   | %     | T <sub>A</sub> =-5°C to +55°C                                                    |
| Line Regulation                                                                                                                                                                                                                                        | $ \Delta V_{BAT}/V_{BAT} $<br>/ΔV <sub>DD</sub> | —    | 0.09 | 0.30 | %/V   | V <sub>DD</sub> =[V <sub>REG</sub> (Typ)+1V] to 6V<br>I <sub>OUT</sub> =10 mA    |
| Load Regulation                                                                                                                                                                                                                                        | ΔV <sub>BAT</sub> /V <sub>BAT</sub>             | —    | 0.09 | 0.30 | %     | I <sub>OUT</sub> =10 mA to 50 mA<br>V <sub>DD</sub> =[V <sub>REG</sub> (Typ)+1V] |
| Supply Ripple Attenuation                                                                                                                                                                                                                              | PSRR                                            | —    | 52   | —    | dB    | I <sub>OUT</sub> =10 mA, 10 Hz to 1 kHz                                          |
|                                                                                                                                                                                                                                                        |                                                 | —    | 47   | —    | dB    | I <sub>OUT</sub> =10 mA, 10 Hz to 10 kHz                                         |
|                                                                                                                                                                                                                                                        |                                                 | —    | 22   | —    | dB    | I <sub>OUT</sub> =10 mA, 10 Hz to 1 MHz                                          |
| Current Regulation (Fast Charge Constant-Current Mode)                                                                                                                                                                                                 |                                                 |      |      |      |       |                                                                                  |
| Fast Charge Current Regulation                                                                                                                                                                                                                         | I <sub>REG</sub>                                | —    | 85   | —    | mA    | MCP73811 - PROG = Low                                                            |
|                                                                                                                                                                                                                                                        |                                                 | —    | 450  | —    | mA    | MCP73811 - PROG = High                                                           |
|                                                                                                                                                                                                                                                        |                                                 | —    | 50   | —    | mA    | MCP73812 - PROG = 20 kΩ                                                          |
|                                                                                                                                                                                                                                                        |                                                 | —    | 100  | —    | mA    | MCP73812 - PROG = 10 kΩ                                                          |
|                                                                                                                                                                                                                                                        |                                                 | —    | 500  | —    | mA    | MCP73812 - PROG = 2 kΩ                                                           |
| Charge Current Tolerance                                                                                                                                                                                                                               | I <sub>RTOL</sub>                               | -10  | —    | +10  | %     | T <sub>A</sub> =-5°C to +55°C                                                    |
| Pass Transistor ON-Resistance                                                                                                                                                                                                                          |                                                 |      |      |      |       |                                                                                  |
| ON-Resistance                                                                                                                                                                                                                                          | R <sub>DSON</sub>                               | —    | 400  | —    | mΩ    | V <sub>DD</sub> = 3.75V, T <sub>J</sub> = 105°C                                  |
| Battery Discharge Current                                                                                                                                                                                                                              |                                                 |      |      |      |       |                                                                                  |
| Output Reverse Leakage Current                                                                                                                                                                                                                         | I <sub>DISCHARGE</sub>                          | —    | 0.5  | 2    | μA    | Shutdown<br>(V <sub>DD</sub> ≤ V <sub>BAT</sub> - 100 mV)                        |

# MCP73811/2

## DC CHARACTERISTICS (Continued)

| <b>Electrical Specifications:</b> Unless otherwise indicated, all limits apply for $V_{DD} = [V_{REG}(typ.) + 0.3V]$ to 6V, $T_A = -40^{\circ}C$ to $+85^{\circ}C$ . Typical values are at $+25^{\circ}C$ , $V_{DD} = [V_{REG}(typ.) + 1.0V]$ |              |                          |                           |                           |             |                                                      |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------|--------------------------|---------------------------|---------------------------|-------------|------------------------------------------------------|
| Parameters                                                                                                                                                                                                                                    | Sym          | Min                      | Typ                       | Max                       | Units       | Conditions                                           |
| <b>Charge Enable (CE), PROG Input - MCP73811</b>                                                                                                                                                                                              |              |                          |                           |                           |             |                                                      |
| Input High Voltage Level                                                                                                                                                                                                                      | $V_{IH}$     | 2                        | —                         | —                         | V           |                                                      |
| Input Low Voltage Level                                                                                                                                                                                                                       | $V_{IL}$     | —                        | —                         | 0.8                       | V           |                                                      |
| Input Leakage Current                                                                                                                                                                                                                         | $I_{LK}$     | —                        | 0.01                      | 1                         | $\mu A$     | $V_{CE} = V_{DD}$ , $V_{PROG} = V_{DD}$              |
| <b>PROG Input - MCP73812</b>                                                                                                                                                                                                                  |              |                          |                           |                           |             |                                                      |
| Charge Impedance Range                                                                                                                                                                                                                        | $R_{PROG}$   | 2                        | —                         | 20                        | $k\Omega$   | MCP73812                                             |
| <b>Automatic Power Down (Direction Control)</b>                                                                                                                                                                                               |              |                          |                           |                           |             |                                                      |
| Automatic Power Down Entry Threshold                                                                                                                                                                                                          | $V_{PD}$     | $V_{BAT} + 10\text{ mV}$ | $V_{BAT} + 50\text{ mV}$  | —                         | V           | $2.3V \leq V_{BAT} \leq V_{REG}$<br>$V_{DD}$ Falling |
| Automatic Power Down Exit Threshold                                                                                                                                                                                                           | $V_{PDEXIT}$ | —                        | $V_{BAT} + 150\text{ mV}$ | $V_{BAT} + 250\text{ mV}$ | V           | $2.3V \leq V_{BAT} \leq V_{REG}$<br>$V_{DD}$ Rising  |
| <b>Thermal Shutdown</b>                                                                                                                                                                                                                       |              |                          |                           |                           |             |                                                      |
| Die Temperature                                                                                                                                                                                                                               | $T_{SD}$     | —                        | 150                       | —                         | $^{\circ}C$ |                                                      |
| Die Temperature Hysteresis                                                                                                                                                                                                                    | $T_{SDHYS}$  | —                        | 10                        | —                         | $^{\circ}C$ |                                                      |


## TEMPERATURE SPECIFICATIONS

| <b>Electrical Specifications:</b> Unless otherwise indicated, all limits apply for $V_{DD} = [V_{REG}(typ.) + 0.3V]$ to 6V. Typical values are at $+25^{\circ}C$ , $V_{DD} = [V_{REG}(typ.) + 1.0V]$ |               |     |     |      |               |                                                   |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------|-----|-----|------|---------------|---------------------------------------------------|
| Parameters                                                                                                                                                                                           | Sym           | Min | Typ | Max  | Units         | Conditions                                        |
| <b>Temperature Ranges</b>                                                                                                                                                                            |               |     |     |      |               |                                                   |
| Specified Temperature Range                                                                                                                                                                          | $T_A$         | -40 | —   | +85  | $^{\circ}C$   |                                                   |
| Operating Temperature Range                                                                                                                                                                          | $T_J$         | -40 | —   | +125 | $^{\circ}C$   |                                                   |
| Storage Temperature Range                                                                                                                                                                            | $T_A$         | -65 | —   | +150 | $^{\circ}C$   |                                                   |
| <b>Thermal Package Resistances</b>                                                                                                                                                                   |               |     |     |      |               |                                                   |
| Thermal Resistance, 5-Lead, SOT-23                                                                                                                                                                   | $\theta_{JA}$ | —   | 230 | —    | $^{\circ}C/W$ | 4-Layer JC51-7 Standard Board, Natural Convection |


## 2.0 TYPICAL PERFORMANCE CURVES

**Note:** The graphs and tables provided following this note are a statistical summary based on a limited number of samples and are provided for informational purposes only. The performance characteristics listed herein are not tested or guaranteed. In some graphs or tables, the data presented may be outside the specified operating range (e.g., outside specified power supply range) and therefore outside the warranted range.


**Note:** Unless otherwise indicated,  $V_{DD} = [V_{REG}(typ.) + 1V]$ ,  $I_{OUT} = 10\text{ mA}$  and  $T_A = +25^\circ\text{C}$ , Constant-voltage mode.




**FIGURE 2-1:** Battery Regulation Voltage ( $V_{BAT}$ ) vs. Supply Voltage ( $V_{DD}$ ).




**FIGURE 2-4:** Charge Current ( $I_{OUT}$ ) vs. Supply Voltage ( $V_{DD}$ ) - MCP73811.




**FIGURE 2-2:** Battery Regulation Voltage ( $V_{BAT}$ ) vs. Ambient Temperature ( $T_A$ ).



**FIGURE 2-5:** Charge Current ( $I_{OUT}$ ) vs. Supply Voltage ( $V_{DD}$ ) - MCP73811.



**FIGURE 2-3:** Output Leakage Current ( $I_{DISCHARGE}$ ) vs. Battery Regulation Voltage ( $V_{BAT}$ ).




**FIGURE 2-6:** Charge Current ( $I_{OUT}$ ) vs. Ambient Temperature ( $T_A$ ) - MCP73811.


# MCP73811/2

## Typical Performance Curves (Continued)


**Note:** Unless otherwise indicated,  $V_{DD} = [V_{REG}(typ.) + 1V]$ ,  $I_{OUT} = 10\text{ mA}$  and  $T_A = +25^\circ\text{C}$ , Constant-voltage mode.




**FIGURE 2-7:** Charge Current ( $I_{OUT}$ ) vs. Ambient Temperature ( $T_A$ ) - MCP73811.




**FIGURE 2-10:** Charge Current ( $I_{OUT}$ ) vs. Supply Voltage ( $V_{DD}$ ) - MCP73812.




**FIGURE 2-8:** Charge Current ( $I_{OUT}$ ) vs. Programming Resistor ( $R_{PROG}$ ) - MCP73812.



**FIGURE 2-11:** Charge Current ( $I_{OUT}$ ) vs. Ambient Temperature ( $T_A$ ) - MCP73812.




**FIGURE 2-9:** Charge Current ( $I_{OUT}$ ) vs. Supply Voltage ( $V_{DD}$ ) - MCP73812.




**FIGURE 2-12:** Charge Current ( $I_{OUT}$ ) vs. Ambient Temperature ( $T_A$ ) - MCP73812.

## Typical Performance Curves (Continued)


**Note:** Unless otherwise indicated,  $V_{DD} = [V_{REG}(typ.) + 1V]$ ,  $I_{OUT} = 10\text{ mA}$  and  $T_A = +25^\circ\text{C}$ , Constant-voltage mode.




**FIGURE 2-13:** Charge Current ( $I_{OUT}$ ) vs. Junction Temperature ( $T_J$ ) - MCP73812.




**FIGURE 2-16:** Power Supply Ripple Rejection (PSRR).




**FIGURE 2-14:** Charge Current ( $I_{OUT}$ ) vs. Junction Temperature ( $T_J$ ) - MCP73812.



**FIGURE 2-17:** Line Transient Response.



**FIGURE 2-15:** Power Supply Ripple Rejection (PSRR).




**FIGURE 2-18:** Line Transient Response.


# MCP73811/2

## Typical Performance Curves (Continued)


**Note:** Unless otherwise indicated,  $V_{DD} = [V_{REG}(typ.) + 1V]$ ,  $I_{OUT} = 10\text{ mA}$  and  $T_A = +25^\circ\text{C}$ , Constant-voltage mode.



**FIGURE 2-19:** Load Transient Response.



**FIGURE 2-21:** Typical Charge Profile (950 mAh) Li-Ion Battery.



**FIGURE 2-20:** Load Transient Response.

## 3.0 PIN DESCRIPTION

The descriptions of the pins are listed in Table 3-1.

**TABLE 3-1: PIN FUNCTION TABLES**

| Pin Number | Symbol           | Function                                         |
|------------|------------------|--------------------------------------------------|
| SOT-23-5   |                  |                                                  |
| 1          | CE               | Active High Charge Enable                        |
| 2          | V <sub>SS</sub>  | Battery Management 0V Reference                  |
| 3          | V <sub>BAT</sub> | Battery Charge Control Output                    |
| 4          | V <sub>DD</sub>  | Battery Management Input Supply                  |
| 5          | PROG             | Current Regulation Set and Charge Control Enable |

### 3.1 Charge Enable Input (CE)

A logic High enables battery charging. A logic Low disables battery charging. The charge enable input is compatible with 1.8V logic.

### 3.2 Battery Management 0V Reference (V<sub>SS</sub>)

Connect to negative terminal of battery and input supply.

### 3.3 Battery Charge Control Output (V<sub>BAT</sub>)

Connect to positive terminal of battery. Drain terminal of internal P-channel MOSFET pass transistor. Bypass to V<sub>SS</sub> with a minimum of 1  $\mu$ F to ensure loop stability when the battery is disconnected.

### 3.4 Battery Management Input Supply (V<sub>DD</sub>)

A supply voltage of [V<sub>REG</sub> (typ.) + 0.3V] to 6V is recommended. Bypass to V<sub>SS</sub> with a minimum of 1  $\mu$ F.

### 3.5 Current Regulation Set (PROG)

For the MCP73811, the current regulation set input (PROG) functions as a digital input selection. A logic Low selects a 85 mA charge current; a logic High selects a 450 mA charge current.

For the MCP73812, the charge current is set by placing a resistor from PROG to V<sub>SS</sub>.

# MCP73811/2

## 4.0 DEVICE OVERVIEW

The MCP73811/2 are simple, but fully integrated linear charge management controllers. Figure 4-1 depicts the operational flow algorithm.




FIGURE 4-1: Flow Chart.

### 4.1 Undervoltage Lockout (UVLO)

The MCP73811/2 does not have an internal under voltage lockout (UVLO) circuit.

### 4.2 Charge Qualification

When the input power is applied, the input supply must rise 150 mV above the battery voltage before the MCP73811/2 becomes operational.

The automatic power down circuit places the device in a shutdown mode if the input supply falls to within +50 mV of the battery voltage.

The automatic circuit is always active. Whenever the input supply is within +50 mV of the voltage at the  $V_{BAT}$  pin, the MCP73811/2 is placed in a shutdown mode.

During power down condition, the battery reverse discharge current is less than 2  $\mu A$ .

For a charge cycle to begin, the automatic power down conditions must be met and the charge enable input must be above the input high threshold.

## 4.3 PRECONDITIONING

The MCP73811/2 does not support preconditioning of deeply depleted cells.

### 4.4 Constant Current MODE - Fast Charge

During the constant current mode, the selected (MCP73811) or programmed (MCP73812) charge current is supplied to the battery or load.

For the MCP73812, the charge current is established using a single resistor from PROG to  $V_{SS}$ . The program resistor and the charge current are calculated using the following equation:

#### EQUATION 4-1:

$$I_{REG} = \frac{1000V}{R_{PROG}}$$

Where:

|            |   |              |
|------------|---|--------------|
| $R_{PROG}$ | = | kilo-ohms    |
| $I_{REG}$  | = | milliamperes |

Constant current mode is maintained until the voltage at the  $V_{BAT}$  pin reaches the regulation voltage,  $V_{REG}$ .

### 4.5 Constant Voltage Mode

When the voltage at the  $V_{BAT}$  pin reaches the regulation voltage,  $V_{REG}$ , constant voltage regulation begins. The regulation voltage is factory set to 4.20V with a tolerance of  $\pm 1.0\%$ .

### 4.6 Charge Termination


The charge cycle is terminated by removing the battery from the charger, removing input power, or driving the charge enable input (CE) to a logic Low. An automatic charge termination method is not implemented.

### 4.7 Automatic Recharge

The MCP73811/2 does not support automatic recharge cycles since automatic charge termination has not been implemented. In essence, the MCP73811/2 is always in a charge cycle whenever the qualification parameters have been met.

## 4.8 Thermal Regulation

The MCP73811/2 limits the charge current based on the die temperature. The thermal regulation optimizes the charge cycle time while maintaining device reliability. Figure 4-2 depicts the thermal regulation for the MCP73811/2.



**FIGURE 4-2:** Thermal Regulation.

## 4.9 Thermal Shutdown

The MCP73811/2 suspends charge if the die temperature exceeds 150°C. Charging will resume when the die temperature has cooled by approximately 10°C. The thermal shutdown is a secondary safety feature in the event that there is a failure within the thermal regulation circuitry.

## 5.0 DETAILED DESCRIPTION

### 5.1 Analog Circuitry

#### 5.1.1 BATTERY MANAGEMENT INPUT SUPPLY ( $V_{DD}$ )

The  $V_{DD}$  input is the input supply to the MCP73811/2. The MCP73811/2 automatically enters a Power-down mode if the voltage on the  $V_{DD}$  input falls to within +50 mV of the battery voltage. This feature prevents draining the battery pack when the  $V_{DD}$  supply is not present.

#### 5.1.2 MCP73812 CURRENT REGULATION SET (PROG)

For the MCP73812, the charge current regulation can be scaled by placing a programming resistor ( $R_{PROG}$ ) from the PROG input to  $V_{SS}$ . The program resistor and the charge current are calculated using the following equation:

#### EQUATION 5-1:

$$I_{REG} = \frac{1000V}{R_{PROG}}$$

Where:

$$\begin{aligned} R_{PROG} &= \text{kilo-ohms} \\ I_{REG} &= \text{milliamperes} \end{aligned}$$

#### 5.1.3 BATTERY CHARGE CONTROL OUTPUT ( $V_{BAT}$ )

The battery charge control output is the drain terminal of an internal P-channel MOSFET. The MCP73811/2 provides constant current and voltage regulation to the battery pack by controlling this MOSFET in the linear region. The battery charge control output should be connected to the positive terminal of the battery pack.

## 5.2 Digital Circuitry

### 5.2.1 CHARGE ENABLE (CE)

The charge enable input pin (CE) can be used to terminate a charge at any time during the charge cycle, as well as to initiate a charge cycle or initiate a recharge cycle.

Driving the input to a logic High enables the device. Driving the input to a logic Low disables the device and terminates a charge cycle. When disabled, the device's supply current is reduced to 50  $\mu$ A, typically.


### 5.2.2 MCP73811 CURRENT REGULATION SELECT (PROG)

For the MCP73811, driving the PROG input to a logic Low selects the low charge current setting (85 mA). Driving the PROG input to a logic High selects the high charge current setting (450 mA).


## 6.0 APPLICATIONS

The MCP73811/2 is designed to operate in conjunction with a host microcontroller or in stand-alone applications. The MCP73811/2 provides the preferred

charge algorithm for Lithium-Ion and Lithium-Polymer cells Constant-current followed by Constant-voltage. [Figure 6-1](#) depicts a typical stand-alone application circuit, while [Figures 6-2](#) depict the accompanying charge profile.



**FIGURE 6-1:** Typical Application Circuit.



**FIGURE 6-2:** Typical Charge Profile (950 mAh Li-Ion Battery).

## 6.1 Application Circuit Design

Due to the low efficiency of linear charging, the most important factors are thermal design and cost, which are a direct function of the input voltage, output current and thermal impedance between the battery charger and the ambient cooling air. The worst-case situation is when the device has transitioned from the Preconditioning mode to the Constant-current mode. In this situation, the battery charger has to dissipate the maximum power. A trade-off must be made between the charge current, cost and thermal requirements of the charger.

### 6.1.1 COMPONENT SELECTION

Selection of the external components in [Figure 6-1](#) is crucial to the integrity and reliability of the charging system. The following discussion is intended as a guide for the component selection process.

#### 6.1.1.1 Charge Current

The preferred fast charge current for Lithium-Ion cells is at the 1C rate, with an absolute maximum current at the 2C rate. For example, a 500 mAh battery pack has a preferred fast charge current of 500 mA. Charging at this rate provides the shortest charge cycle times without degradation to the battery pack performance or life.

# MCP73811/2

## 6.1.1.2 Thermal Considerations

The worst-case power dissipation in the battery charger occurs when the input voltage is at the maximum and the device has transitioned from the Preconditioning mode to the Constant-current mode. In this case, the power dissipation is:

### EQUATION 6-1:

$$PowerDissipation = (V_{DDMAX} - V_{PTHMIN}) \times I_{REGMAX}$$

Where:

- $V_{DDMAX}$  = the maximum input voltage
- $I_{REGMAX}$  = the maximum fast charge current
- $V_{PTHMIN}$  = the minimum transition threshold voltage

Power dissipation with a 5V,  $\pm 10\%$  input voltage source is:

### EQUATION 6-2:

$$PowerDissipation = (5.5V - 2.7V) \times 500mA = 1.4W$$

This power dissipation with the battery charger in the SOT-23-5 package will cause thermal regulation to be entered as depicted in [Figure 6-3](#).

## 6.1.1.3 External Capacitors

The MCP73811/2 is stable with or without a battery load. In order to maintain good AC stability in the Constant-voltage mode, a minimum capacitance of 1  $\mu F$  is recommended to bypass the  $V_{BAT}$  pin to  $V_{SS}$ . This capacitance provides compensation when there is no battery load. In addition, the battery and interconnections appear inductive at high frequencies. These elements are in the control feedback loop during Constant-voltage mode. Therefore, the bypass capacitance may be necessary to compensate for the inductive nature of the battery pack.

Virtually any good quality output filter capacitor can be used, independent of the capacitor's minimum Effective Series Resistance (ESR) value. The actual value of the capacitor (and its associated ESR) depends on the output load current. A 1  $\mu F$  ceramic, tantalum or aluminum electrolytic capacitor at the output is usually sufficient to ensure stability for output currents up to a 500 mA.

## 6.1.1.4 Reverse-Blocking Protection

The MCP73811/2 provides protection from a faulted or shorted input. Without the protection, a faulted or shorted input would discharge the battery pack through the body diode of the internal pass transistor.

## 6.1.1.5 Charge Inhibit


The charge enable input pin (CE) can be used to terminate a charge at any time during the charge cycle, as well as to initiate a charge cycle or initiate a recharge cycle.

Driving the input to a logic High enables the device. Driving the input to a logic Low disables the device and terminates a charge cycle. When disabled, the device's supply current is reduced to 50  $\mu A$ , typically.


## 6.2 PCB Layout Issues

For optimum voltage regulation, place the battery pack as close as possible to the device's  $V_{BAT}$  and  $V_{SS}$  pins, recommended to minimize voltage drops along the high current-carrying PCB traces.

If the PCB layout is used as a heatsink, adding many vias in the heatsink pad can help conduct more heat to the backplane of the PCB, thus reducing the maximum junction temperature. [Figures 6-3](#) and [6-4](#) depict a typical layout with PCB heatsinking.




**FIGURE 6-3:** Typical Layout (Top).



**FIGURE 6-4:** Typical Layout (Bottom).


## 7.0 PACKAGE INFORMATION

### 7.1 Package Marking Information



| Standard *        |      |
|-------------------|------|
| Part Number       | Code |
| MCP73811T-420I/OT | KSNN |
| MCP73812T-420I/OT | KWNN |

Example:



\* Custom output voltages available upon request.

Contact your local Microchip sales office for more information.


|                |        |                                                                                                                  |
|----------------|--------|------------------------------------------------------------------------------------------------------------------|
| <b>Legend:</b> | XX...X | Customer-specific information                                                                                    |
|                | Y      | Year code (last digit of calendar year)                                                                          |
|                | YY     | Year code (last 2 digits of calendar year)                                                                       |
|                | WW     | Week code (week of January 1 is week '01')                                                                       |
|                | NNN    | Alphanumeric traceability code                                                                                   |
|                | (e3)   | Pb-free JEDEC designator for Matte Tin (Sn)                                                                      |
|                | *      | This package is Pb-free. The Pb-free JEDEC designator (e3) can be found on the outer packaging for this package. |

**Note:** In the event the full Microchip part number cannot be marked on one line, it will be carried over to the next line, thus limiting the number of available characters for customer-specific information.

# MCP73811/2

## 5-Lead Plastic Small Outline Transistor (OT) [SOT-23]

**Note:** For the most current package drawings, please see the Microchip Packaging Specification located at <http://www.microchip.com/packaging>



|                          |    | Units | MILLIMETERS |     |      |
|--------------------------|----|-------|-------------|-----|------|
| Dimension Limits         |    |       | MIN         | NOM | MAX  |
| Number of Pins           | N  |       | 5           |     |      |
| Lead Pitch               | e  |       | 0.95 BSC    |     |      |
| Outside Lead Pitch       | e1 |       | 1.90 BSC    |     |      |
| Overall Height           | A  |       | 0.90        | —   | 1.45 |
| Molded Package Thickness | A2 |       | 0.89        | —   | 1.30 |
| Standoff                 | A1 |       | 0.00        | —   | 0.15 |
| Overall Width            | E  |       | 2.20        | —   | 3.20 |
| Molded Package Width     | E1 |       | 1.30        | —   | 1.80 |
| Overall Length           | D  |       | 2.70        | —   | 3.10 |
| Foot Length              | L  |       | 0.10        | —   | 0.60 |
| Footprint                | L1 |       | 0.35        | —   | 0.80 |
| Foot Angle               | φ  |       | 0°          | —   | 30°  |
| Lead Thickness           | c  |       | 0.08        | —   | 0.26 |
| Lead Width               | b  |       | 0.20        | —   | 0.51 |

**Notes:**

1. Dimensions D and E1 do not include mold flash or protrusions. Mold flash or protrusions shall not exceed 0.127 mm per side.
2. Dimensioning and tolerancing per ASME Y14.5M.

BSC: Basic Dimension. Theoretically exact value shown without tolerances.

Microchip Technology Drawing C04-091B

## APPENDIX A: REVISION HISTORY

### Revision B (September 2007)

The following is the list of modifications:

1. Modified "No End-of-Charge Control" bullet to read "External End-of-Charge Control".
2. Deleted No Undervoltage Lockout (UVLO) bullet
3. Replaced Figure 2-21 with new plot and changed figure caption.
4. Deleted Figure 2-22.
5. Replaced Figure 6-2 with new plot and changed figure caption.
6. Deleted Figure 6-3.
7. Updated revision history.

### Revision A (March 2007)

- Original Release of this Document.

# MCP73811/2

---

NOTES:

## PRODUCT IDENTIFICATION SYSTEM

To order or obtain information, e.g., on pricing or delivery, refer to the factory or the listed sales office.

| <u>PART NO.</u>                                                                                                                                                                                                                                                                                                                                                                                                       | — | <u>XXX</u>      | <u>X</u>    | <u>/XX</u> |
|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---|-----------------|-------------|------------|
| Device                                                                                                                                                                                                                                                                                                                                                                                                                |   | Voltage Options | Temperature | Package    |
| <div> <div> Device: MCP73811T: Li-Ion Charger w/Selectable Charge Current, Tape and Reel<br/> MCP73812T: Li-Ion Charger w/Selectable Charge Current, Tape and Reel </div> <div> Voltage Options *: 420 = 4.2V "Standard"<br/> *Contact factory for other output voltage options. </div> <div> Temperature: I = -40°C to +85°C </div> <div> Package Type: OT = Small Outline Transistor (SOT-23), 5-lead </div> </div> |   |                 |             |            |
| <b>Examples:</b><br>a) MCP73811T-420I/OT: 4.2V Charger SOT-23-5 pkg.<br>a) MCP73812T-420I/OT: 4.2V Charger SOT-23-5 pkg.                                                                                                                                                                                                                                                                                              |   |                 |             |            |

# MCP73811/2

---

NOTES:

---

**Note the following details of the code protection feature on Microchip devices:**

- Microchip products meet the specification contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is one of the most secure families of its kind on the market today, when used in the intended manner and under normal conditions.
- There are dishonest and possibly illegal methods used to breach the code protection feature. All of these methods, to our knowledge, require using the Microchip products in a manner outside the operating specifications contained in Microchip's Data Sheets. Most likely, the person doing so is engaged in theft of intellectual property.
- Microchip is willing to work with the customer who is concerned about the integrity of their code.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of their code. Code protection does not mean that we are guaranteeing the product as "unbreakable."

Code protection is constantly evolving. We at Microchip are committed to continuously improving the code protection features of our products. Attempts to break Microchip's code protection feature may be a violation of the Digital Millennium Copyright Act. If such acts allow unauthorized access to your software or other copyrighted work, you may have a right to sue for relief under that Act.

---

Information contained in this publication regarding device applications and the like is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION, INCLUDING BUT NOT LIMITED TO ITS CONDITION, QUALITY, PERFORMANCE, MERCHANTABILITY OR FITNESS FOR PURPOSE. Microchip disclaims all liability arising from this information and its use. Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights.

#### **Trademarks**

The Microchip name and logo, the Microchip logo, Accuron, dsPIC, KEELOQ, KEELOQ logo, microID, MPLAB, PIC, PICmicro, PICSTART, PRO MATE, rPIC and SmartShunt are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

AmpLab, FilterLab, Linear Active Thermistor, Migratable Memory, MXDEV, MXLAB, SEEVAL, SmartSensor and The Embedded Control Solutions Company are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Analog-for-the-Digital Age, Application Maestro, CodeGuard, dsPICDEM, dsPICDEM.net, dsPICworks, dsSPEAK, ECAN, ECONOMONITOR, FanSense, FlexROM, fuzzyLAB, In-Circuit Serial Programming, ICSP, ICEPIC, Mindi, MiWi, MPASM, MPLAB Certified logo, MPLIB, MPLINK, PICkit, PICDEM, PICDEM.net, PICLAB, PICtail, PowerCal, PowerInfo, PowerMate, PowerTool, REAL ICE, rLAB, Select Mode, Smart Serial, SmartTel, Total Endurance, UNI/O, WiperLock and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

All other trademarks mentioned herein are property of their respective companies.

© 2007, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.

 Printed on recycled paper.

**QUALITY MANAGEMENT SYSTEM**  
**CERTIFIED BY DNV**  
**== ISO/TS 16949:2002 ==**

*Microchip received ISO/TS-16949:2002 certification for its worldwide headquarters, design and wafer fabrication facilities in Chandler and Tempe, Arizona; Gresham, Oregon and design centers in California and India. The Company's quality system processes and procedures are for its PIC® MCUs and dsPIC® DSCs, KEELOQ® code hopping devices, Serial EEPROMs, microperipherals, nonvolatile memory and analog products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001:2000 certified.*



---

## WORLDWIDE SALES AND SERVICE

---

### AMERICAS

#### Corporate Office

2355 West Chandler Blvd.  
Chandler, AZ 85224-6199  
Tel: 480-792-7200  
Fax: 480-792-7277  
Technical Support:  
<http://support.microchip.com>  
Web Address:  
[www.microchip.com](http://www.microchip.com)

#### Atlanta

Duluth, GA  
Tel: 678-957-9614  
Fax: 678-957-1455

#### Boston

Westborough, MA  
Tel: 774-760-0087  
Fax: 774-760-0088

#### Chicago

Itasca, IL  
Tel: 630-285-0071  
Fax: 630-285-0075

#### Dallas

Addison, TX  
Tel: 972-818-7423  
Fax: 972-818-2924

#### Detroit

Farmington Hills, MI  
Tel: 248-538-2250  
Fax: 248-538-2260

#### Kokomo

Kokomo, IN  
Tel: 765-864-8360  
Fax: 765-864-8387

#### Los Angeles

Mission Viejo, CA  
Tel: 949-462-9523  
Fax: 949-462-9608

#### Santa Clara

Santa Clara, CA  
Tel: 408-961-6444  
Fax: 408-961-6445

#### Toronto

Mississauga, Ontario,  
Canada  
Tel: 905-673-0699  
Fax: 905-673-6509

### ASIA/PACIFIC

#### Asia Pacific Office

Suites 3707-14, 37th Floor  
Tower 6, The Gateway  
Harbour City, Kowloon  
Hong Kong  
Tel: 852-2401-1200  
Fax: 852-2401-3431

#### Australia - Sydney

Tel: 61-2-9868-6733  
Fax: 61-2-9868-6755

#### China - Beijing

Tel: 86-10-8528-2100  
Fax: 86-10-8528-2104

#### China - Chengdu

Tel: 86-28-8665-5511  
Fax: 86-28-8665-7889

#### China - Fuzhou

Tel: 86-591-8750-3506  
Fax: 86-591-8750-3521

#### China - Hong Kong SAR

Tel: 852-2401-1200  
Fax: 852-2401-3431

#### China - Qingdao

Tel: 86-532-8502-7355  
Fax: 86-532-8502-7205

#### China - Shanghai

Tel: 86-21-5407-5533  
Fax: 86-21-5407-5066

#### China - Shenyang

Tel: 86-24-2334-2829  
Fax: 86-24-2334-2393

#### China - Shenzhen

Tel: 86-755-8203-2660  
Fax: 86-755-8203-1760

#### China - Shunde

Tel: 86-757-2839-5507  
Fax: 86-757-2839-5571

#### China - Wuhan

Tel: 86-27-5980-5300  
Fax: 86-27-5980-5118

#### China - Xian

Tel: 86-29-8833-7252  
Fax: 86-29-8833-7256

### ASIA/PACIFIC

#### India - Bangalore

Tel: 91-80-4182-8400  
Fax: 91-80-4182-8422

#### India - New Delhi

Tel: 91-11-4160-8631  
Fax: 91-11-4160-8632

#### India - Pune

Tel: 91-20-2566-1512  
Fax: 91-20-2566-1513

#### Japan - Yokohama

Tel: 81-45-471- 6166  
Fax: 81-45-471-6122

#### Korea - Daegu

Tel: 82-53-744-4301  
Fax: 82-53-744-4302

#### Korea - Seoul

Tel: 82-2-554-7200  
Fax: 82-2-558-5932 or  
82-2-558-5934

#### Malaysia - Penang

Tel: 60-4-646-8870  
Fax: 60-4-646-5086

#### Philippines - Manila

Tel: 63-2-634-9065  
Fax: 63-2-634-9069

#### Singapore

Tel: 65-6334-8870  
Fax: 65-6334-8850

#### Taiwan - Hsin Chu

Tel: 886-3-572-9526  
Fax: 886-3-572-6459

#### Taiwan - Kaohsiung

Tel: 886-7-536-4818  
Fax: 886-7-536-4803

#### Taiwan - Taipei

Tel: 886-2-2500-6610  
Fax: 886-2-2508-0102

#### Thailand - Bangkok

Tel: 66-2-694-1351  
Fax: 66-2-694-1350

### EUROPE

#### Austria - Wels

Tel: 43-7242-2244-39  
Fax: 43-7242-2244-393

#### Denmark - Copenhagen

Tel: 45-4450-2828  
Fax: 45-4485-2829

#### France - Paris

Tel: 33-1-69-53-63-20  
Fax: 33-1-69-30-90-79

#### Germany - Munich

Tel: 49-89-627-144-0  
Fax: 49-89-627-144-44

#### Italy - Milan

Tel: 39-0331-742611  
Fax: 39-0331-466781

#### Netherlands - Drunen

Tel: 31-416-690399  
Fax: 31-416-690340

#### Spain - Madrid

Tel: 34-91-708-08-90  
Fax: 34-91-708-08-91

#### UK - Wokingham

Tel: 44-118-921-5869  
Fax: 44-118-921-5820

06/25/07