

PRODUCTS

Equalizers

- GS1524A
- GS1574A
- GS1674
- GS2964
- GS2974A
- GS2974B
- GS2984
- GS2993
- GS2994
- GS3440
- GS3441
- GS3442
- GS9074A

Analog Video

Audio Extraction/Insertion

Aviia / HDcctv

Bridges

Cable Drivers

Cable Extenders

Clock and Data Recovery

Crosspoint Switches

HD-SD Only SerDes

Laser Modulator Drivers

Legacy Products

Limiting Amplifiers

ROSAs

Re-Drivers

Receivers

Reclockers

SerDes

Sync Separators

Thunderbolt™ Cable Transceivers

Timing

Transimpedance Amplifiers

Transmitters

Video Optical Modules



GS2994 Green Adaptive Cable Equalizer

Optimized for Performance at 270Mb/s, 1.485Gb/s and 2.97Gb/s

Designed to equalize and restore signals received over 75 ? coaxial cable, with power saving features

product information

documentation

Overview

The GS2994 is a high - speed BiCMOS integrated circuit designed to equalize and restore signals received over 75 ? coaxial cable.

The device is designed to support SMPTE 424M, SMPTE292M and SMPTE 259M, and is optimized for performance at 270Mb/s, 1.485Gb/s and 2.97Gb/s.

The GS2994 features DC restoration to compensate for the DC content of SMPTE pathological test patterns.

The Carrier Detect output pin (CD) indicates whether a valid input signal has been detected. It can be connected directly to the SLEEP pin to enable automatic power - down upon loss of carrier. In the manual sleep mode, a voltage programmable threshold, which can be changed via the SQ\_ADJ pin, forces CD high when the input signal amplitude falls below the threshold. This allows the GS2994 to distinguish between low - amplitude SDI signals and noise at the input of the device.

The equalizing and DC restore stages are disengaged when the BYPASS pin is HIGH. No equalization occurs in Bypass mode.

The GS2994 includes a gain selection pin (GAIN\_SEL) which, when tied HIGH, compensates for 6dB flat attenuation.

The differential outputs can be DC - coupled to Gennum 3.3V cable drivers and reclockers and to industry - standard 1.2V, 2.5V and 3.3V CML logic. In general, DC- coupling to any termination voltage between 1.2V and 3.3V is supported.

The GS2994 also includes programmable de - emphasis with three operating levels in order to support long PCB traces. The GS2994 is footprint and drop - in compatible with existing GS2974 and GS2984 designs.

The device is available in a 16 - pin, 4mm x 4mm QFN package. Power consumption of the GS2994 is typically 166mW when DC - coupled at 1.2V.

The GS2994 is Pb - free, and the encapsulation compound does not contain halogenated flame retardant.

...less

Features/Highlights

- ? SMPTE 424M, SMPTE 292M and SMPTE 259M compliant
- ? Automatic cable equalization
- ? Multi - standard operation from 143Mb/s to 2.97Gb/s
- ? Performance optimized for 270Mb/s, 1.485Gb/s and 2.97Gb/s. Typical equalized length of Belden 1694A cable:
  - ? 140m at 2.97Gb/s
  - ? 200m at 1.485Gb/s
  - ? 400m at 270Mb/s
- ? Supports DVB - ASI at 270Mb/s
- ? Manual bypass (useful for low data rates with slow rise/fall times)
- ? Programmable carrier detect with squelch threshold adjustment
- ? Automatic power - down on loss of signal
- ? Standby power <30mW (typical)
- ? Differential output, supports DC - coupling to 1.2V - > 3.3V CML logic
- ? 0/6 dB gain boost selection pin
  - Selectable de - emphasis: 2dB, 4dB and 6dB
- ? Standard EIA/JEDEC logic control and status signal levels
- ? Single 3.3V power supply operation
- ? 166mW power consumption (typical)
- ? Wide operating temperature range of - 40°C to +85 °C
- ? Small footprint QFN package (4mm x 4mm)
  - ? Footprint compatible with the GS2974 and the GS2984
- ? Pb- free and RoHS compliant

...less

Key Applications

- ? SMPTE 424M, SMPTE 292M and SMPTE 259M coaxial cable serial digital interfaces

...less

Ordering Information

Part Number	Package
GS2994 - INE3	16- pin QFN
GS2994 - INTE3	16- pin QFN Tape & Reel (250pcs)
GS2994 - INTE3Z	16- pin QFN Tape & Reel (2500pcs)

...less

BUY/SAMPLE

Order Samples  
Buy from Distributor

STAY CONNECTED

Stay connected with the latest products and news from Gennum

click here

CONTACT

SUPPORT