## Package Drawing





### NOTE: All dimensions in millimeters (mm).

Tri Color				
1	Cathode (Color 1)			
2	Common Anode			
3	Cathode (Color 3)			
4	Cathode (Color 2)			
Bi Color				
1	Cathode (Color 1)			
2	Anode (Color 1)			
3	Cathode (Color 2)			
4	Anode (Color 2)			

### **Device Selection Guide**

### **Bi Color**

Part Number	Color 1	Color 2
HSMF-A201-xxxxx	GaP Red	GaP Yellow Green
HSMF-A202-xxxxx	GaP Red	GaP Yellow
HSMF-A203-xxxxx	GaP Red	GaP Emerald Green
HSMF-A204-xxxxx	GaP Orange	GaP Yellow Green
HSMF-A205-xxxxx	GaP Orange	GaP Emerald Green
HSMF-A206-xxxxx	GaP Yellow	GaP Yellow Green
HSMF-A211-xxxxx	AlGaAs Red	GaP Yellow Green
HSMF-A212-xxxxx	AlGaAs Red	GaP Yellow
HSMF-A222-xxxxx	AllnGaP Red	AllnGaP Amber
HSMF-A226-xxxxx	AllnGaP Amber	AllnGaP Yellow Green

	Color 1			Color 2		
	Min. I <sub>V</sub>	at 20 mA	Typical I <sub>V</sub> at 20 mA	Min. I <sub>V</sub> a	at 20 mA	Typical I <sub>V</sub> at 20 mA
Part Number	Bin ID	(mcd)	(mcd)	Bin ID	(mcd)	(mcd)
HSMF-A201-A00J1	K2	9.0	16.0	L1	11.2	20.0
HSMF-A202-A00J1	K2	9.0	16.0	K1	7.2	12.0
HSMF-A203-A00J1	K2	9.0	16.0	J1	4.5	8.0
HSMF-A204-A00J1	K2	9.0	16.0	L1	11.2	20.0
HSMF-A205-A00J1	K2	9.0	16.0	J1	4.5	8.0
HSMF-A206-A00J1	K2	9.0	16.0	L1	11.2	20.0
HSMF-A211-A00J1	L2	14.0	25.0	L1	11.2	20.0
HSMF-A212-A00J1	L2	14.0	25.0	K1	7.2	12.0
HSMF-A222-A00J1	P1	45.0	80.0	P1	45.0	80.0
HSMF-A226-A00J1	P2	56.0	100.0	M2	22.4	60.0
NOTE: The luminou	us intensity I <sub>V</sub> , is	measured at the	e mechanical axis o	of the lamp packa	age. The actual r	beak of the spatial

radiation pattern may not be aligned with this axis.

**NOTE:**  $I_V$  tolerance = ±10%.

### Tri Color

Part Number	Color 1	Color 2	Color 3
HSMF-A341-xxxxx	AllnGaP Red	InGaN Green	InGaN Blue

	Color 1		Color 2		Color 3				
	Mir @ 20	n. Iv ) mA	Typical Iv @ 20 mA	Mir @ 2	n. Iv 0 mA	Typical Iv @ 20 mA	Mir @ 20	n. lv 0 mA	Typical Iv @ 20 mA
Part Number	Bin ID	(mcd)	(mcd)	Bin ID	(mcd)	(mcd)	Bin ID	(mcd)	(mcd)
	K2	9.0	13.0	L2	14.0	20.0	K2	9.2	10.0
	P1	45.0	80.0	R1	112.5	160.0	K2	9.2	10.0
HSMF-A341-A00J1	P1	45.0	80.0	R1	112.5	160.0	K2	9.2	10.0
	P1	45.0	80.0	R1	112.5	160.0	N1	28.5	40.0
	P1	45.0	80.0	R1	112.5	160.0	N1	28.5	40.0
<b>NOTE:</b> The luminous intensity I <sub>V</sub> , is measured at the mechanical axis of the lamp package. The actual peak of the spatial radiation pattern may not be aligned with this axis.									
NOTE: I <sub>V</sub> tolerand	<b>NOTE:</b> $I_V$ tolerance = ±10%.								

### **Part Numbering System**



### Absolute Maximum Ratings (T<sub>A</sub> = 25°C)

		AllnGaP					
Parameters	GaP	AlGaAs	Red, Amber	Yellow Green	GaN/InGaN		
DC Forward Current <sup>a</sup>	30 mA	30 mA	30 mA <sup>b,c</sup>	20 mA <sup>c</sup>	20 mA		
Peak Forward Current <sup>d</sup>	100 mA	100 mA	100 mA	100 mA	100 mA		
Power Dissipation	78 mW	78 mW	72 mW	48 mW	120 mW		
Reverse Voltage		5V					
Junction Temperature		110°C					
Operating Temperature		–55°C to +100°C					
Storage Temperature			–55°C to +100°C				

a. Derate linearly as shown in figure 4.

b. Drive Current between 10 mA and 30 mA are recommended for best long-term performance.

c. Operation at current below 5 mA is not recommended.

d. Duty factor = 10%, Frequency = 1 kHz.

### Optical Characteristics ( $T_A = 25^{\circ}C$ )

	Peak Wavelength λ <sub>ΡΕΔΚ</sub> (nm)	Dominant Wavelength λ <sub>D</sub> (nm) <sup>a</sup>	Viewing Angle 20 <sub>1/2</sub> (Degrees) <sup>b</sup>	Luminous Efficacy η <sub>ν</sub> (Im/W) <sup>c</sup>	Luminous Intensity/ Total Flux I <sub>v</sub> (mcd)/φ <sub>v</sub> (mlm)
Color	Тур.	Тур.	Тур.	Тур.	Тур.
GaP Red	635	626	120	120	0.45
AlGaAs Red	645	637	120	63	0.45
AllnGaP Red	635	626	120	150	0.45
AllnGaP Red Orange	621	615	120	240	0.45
GaP Orange	600	602	120	380	0.45
AllnGaP Amber	592	590	120	480	0.45
GaP Yellow	583	585	120	580	0.45
AllnGaP Amber	592	590	120	480	0.45
GaP Yellow Green	565	569	120	590	0.45
GaP Emerald Green	558	560	120	650	0.45
InGaN Green	523	525	120	500	0.45
InGaN Blue	468	470	120	75	0.45
GaN Blue	428	462	120	65	0.45
AllnGaP Yellow Green	575	571	120	620	0.45

a. The dominant wavelength,  $\lambda_D$ , is derived from the CIE Chromaticity Diagram and represents the color of the device.

b.  $\theta_{1/2}$  is the off-axis angle where the luminous intensity is 1/2 the peak intensity.

c. Radiant intensity,  $I_e$  in watts/steradian, may be calculated from the equation  $I_e = I_v/\eta_v$ , where  $I_v$  is the luminous intensity in candelas and  $\eta_v$  is the luminous efficacy in lumens/watt.

## Electrical Characteristics ( $T_A = 25^{\circ}C$ )

	Forward Voltage V <sub>F</sub> (Volts) @ I <sub>F</sub> = 20 mA		Reverse Voltage V <sub>R</sub> @ 100 μΑ	Reverse Voltage V <sub>R</sub> @ 10 μΑ
Dice Technology	Тур.	Max.	Min.	Min.
GaP	2.2	2.6	5	—
AS AlGaAs	1.9	2.6	5	—
AllnGaP	1.9	2.4	5	—
GaN Blue	3.9	4.3	—	5
InGaN	3.4	4.05	—	5

Figure 1: Relative Intensity vs. Wavelength



Broadcom

#### Figure 2: Forward Current vs. Forward Voltage



Figure 3: Relative Intensity vs. Forward Voltage



Figure 4: Maximum Forward Current vs. Ambient Temperature. Derated based on  $T_JMAX = 110^{\circ}C$ ,  $R\theta_{JA} = 500^{\circ}C/W$  (1 chip on).





### Figure 5: Maximum Forward Current vs. Ambient Temperature. Derated based on $T_JMAX = 110^{\circ}C$ , $R\theta_{JA} = 700^{\circ}C/W$ (3 chip on).







#### Figure 7: Radiation Pattern



Figure 8: Recommended SnPb Reflow Soldering Profile



**NOTE:** For detail information on reflow soldering of Avago surface mount LEDs, refer to Avago Application Note AN 1060 Surface Mounting SMT LED Indicator Components.

#### Figure 9: Recommended Soldering Pad Pattern



#### Figure 10: Tape Leader and Trailer Dimension



USER FEED DIRECTION



Figure 11: Tape Leader and Trailer Dimension

#### Figure 12: Reel Dimension



#### Figure 13: Reeling Orientation



#### Figure 14: Recommended Pick and Place Nozzle Size



**NOTE:** Diameter ID should be bigger than 2.3 mm.

Broadcom

The encapsulation material of the product is made of silicone for better reliability of the product. As silicone is a soft material, please do not press on the silicone or poke a sharp object onto the silicone. These might damage the product and cause premature failure. During assembly of handling, the unit should be held on the body only. Refer to Avago Application Note AN 5288 for detail information.

### **Moisture Sensitivity**

This product is qualified as Moisture Sensitive Level 2a per Jedec J-STD-020. Precautions when handling this moisture sensitive product is important to ensure the reliability of the product. Do refer to Avago Application Note AN5305 Handling of Moisture Sensitive Surface Mount Devices for details.

- 1. Storage before use:
  - Unopen moisture barrier bag (MBB) can be stored at <40°C/90%RH for 12 months. If the actual shelf life has exceeded 12 months and the HIC indicates that baking is not required, then it is safe to reflow the LEDs per the original MSL rating.
  - It is not recommended to open the MBB prior to assembly (as an example, for IQC).
- 2. Control after opening the MBB:
  - The humidity indicator card (HIC) shall be read immediately upon opening of MBB.
  - The LEDs must be kept at <30°C/60%RH at all time and all high temperature related process including soldering, curing or rework need to be completed within 672 hours.
- 3. Control for unfinished reel:
  - For any unuse LEDs, they need to be stored in sealed MBB with desiccant or desiccator at <5%RH.</li>
- 4. Control of assembled boards:
  - If the PCB soldered with the LEDs is to be subjected to other high temperature processes, the PCB need to be stored in sealed MBB with desiccant or desiccator at <5%RH to ensure no LEDs have exceeded their floor life of 672 hours.
- 5. Baking is required if:
  - 10% or 15% HIC indicator turns pink.
  - The LEDs are exposed to condition of >30°C/60% RH at any time.

- The LEDs floor life exceeded 672 hours.

Recommended baking condition: 60 ±5°C for 20 hours.

### I<sub>v</sub> Bin Select (X<sub>5</sub>X<sub>6</sub>)

Individual reel will contain parts from 1 half bin only.

### Table 1: Minimum Intensity Bin Selection for HSMF-A201-xxxxx, HSMF-A204-xxxxx, HSMF-A206-xxxxx

X <sub>5</sub>	Color 1 (Red/ Yellow/Orange)	Color 2 (Green)
A	K2	L1
В	K2	L2
С	K2	M1
D	K2	M2
E	K2	N1
F	L1	L1
G	L1	L2
Н	L1	M1
J	L1	M2
К	L1	N1
L	L2	L1
М	L2	L2
N	L2	M1
Р	L2	M2
Q	L2	N1
R	M1	L1
S	M1	L2
Т	M1	M1
U	M1	M2
V	M1	N1
W	M2	L1
Х	M2	L2
Y	M2	M1
Z	M2	M2
1	M2	N1

## Table 2: Minimum Intensity Bin Selection forHSMF-A202-xxxxx

X <sub>5</sub>	Color 1 (Red)	Color 2 (Yellow)
A	K2	К1
В	K2	К2
С	K2	L1
D	K2	L2

# Table 2: Minimum Intensity Bin Selection forHSMF-A202-xxxxx (Continued)

X <sub>5</sub>	Color 1 (Red)	Color 2 (Yellow)
E	K2	M1
F	L1	K1
G	L1	К2
Н	L1	L1
J	L1	L2
К	L1	M1
L	L2	K1
Μ	L2	K2
N	L2	L1
Р	L2	L2
Q	L2	M1
R	M1	K1
S	M1	K2
Т	M1	L1
U	M1	L2
V	M1	M1
W	M2	K1
Х	M2	K2
Y	M2	L1
Z	M2	L2
1	M2	M1

## Table 3: Minimum Intensity Bin Selection for HSMF-A203-xxxxx and HSMF-A205-xxxxx

X <sub>5</sub>	Color 1 (Red/ Orange)	Color 2 (Green)
A	K2	J1
В	K2	J2
С	K2	K1
D	K2	K2
E	K2	L1
F	L1	J1
G	L1	J2
Н	L1	K1
J	L1	K2
К	L1	L1
L	L2	J1
М	L2	J2
N	L2	K1
Р	L2	К2
Q	L2	L1

## Table 3: Minimum Intensity Bin Selection for HSMF-A203 xxxxx and HSMF-A205-xxxxx (Continued)

X <sub>5</sub>	Color 1 (Red/ Orange)	Color 2 (Green)
R	M1	J1
S	M1	J2
Т	M1	K1
U	M1	K2
V	M1	L1
W	M2	J1
Х	M2	J2
Y	M2	K1
Z	M2	K2
1	M2	L1

# Table 4: Minimum Intensity Bin Selection for HSMF-A211 xxxxxx

X <sub>5</sub>	Color 1 (Red)	Color 2 (Green)
A	L2	L1
В	L2	L2
С	L2	M1
D	L2	M2
E	L2	N1
F	M1	L1
G	M1	L2
Н	M1	M1
J	M1	M2
К	M1	N1
L	M2	L1
М	M2	L2
Ν	M2	M1
Р	M2	M2
Q	M2	N1
R	N1	L1
S	N1	L2
Т	N1	M1
U	N1	M2
V	N1	N1
W	N2	L1
Х	N2	L2
Y	N2	M1
Z	N2	M2
1	N2	N1

Broadcom

#### **NOTE:** 0 represents full distribution.

## Table 5: Minimum Intensity Bin Selection for HSMF-A212 xxxxxx

X <sub>5</sub>	Color 1 (Red)	Color 2 (Yellow)
A	L2	K1
В	L2	К2
С	L2	L1
D	L2	L2
E	L2	M1
F	M1	K1
G	M1	К2
Н	M1	L1
J	M1	L2
К	M1	M1
L	M2	K1
М	M2	K2
N	M2	L1
Р	M2	L2
Q	M2	M1
R	N1	K1
S	N1	K2
Т	N1	L1
U	N1	L2
V	N1	M1
W	N2	K1
Х	N2	K2
Y	N2	L1
Z	N2	L2
1	N2	M1

## Table 6: Minimum Intensity Bin Selection for HSMF-A222 xxxxx

X <sub>5</sub>	Color 1 (Red)	Color 2 (Amber)
A	P1	P1
В	P1	P2
С	P1	Q1
D	P1	Q2
E	P1	R1
F	P2	P1
G	P2	P2
Н	P2	Q1
J	P2	Q2
К	P2	R1

#### Broadcom

## Table 6: Minimum Intensity Bin Selection for HSMF-A222 xxxxx (Continued)

X <sub>5</sub>	Color 1 (Red)	Color 2 (Amber)
L	Q1	P1
М	Q1	P2
Ν	Q1	Q1
Р	Q1	Q2
Q	Q1	R1
R	Q2	P1
S	Q2	P2
Т	Q2	Q1
U	Q2	Q2
V	Q2	R1
W	R1	P1
Х	R1	P2
Y	R1	Q1
Z	R1	Q2
1	R1	R1
2	R2	P1
3	R2	P2
4	R2	Q1
5	R2	Q2
6	R2	R1

# Table 7: Minimum Intensity Bin Selection forHSMF-A341-xxxxx

X <sub>5</sub>	Color 1 (Red/ Red Orange)	Color 2 (Green)	Color 3 (Blue)
A	P1	R1	N1
В	P1	R1	N2
С	P1	R1	P1
D	P1	R2	N1
E	P1	R2	N2
F	P1	R2	P1
G	P1	S1	N1
Н	P1	S1	N2
J	P1	S1	P1
К	P2	R1	N1
L	P2	R1	N2
М	P2	R1	P1
N	P2	R2	N1
Р	P2	R2	N2
Q	P2	R2	P1
R	P2	S1	N1

# Table 7: Minimum Intensity Bin Selection forHSMF-A341-xxxxx (Continued)

X <sub>5</sub>	Color 1 (Red/ Red Orange)	Color 2 (Green)	Color 3 (Blue)
S	P2	S1	N2
Т	P2	S1	P1
U	Q1	R1	N1
V	Q1	R1	N2
W	Q1	R1	P1
Х	Q1	R2	N1
Y	Q1	R2	N2
Z	Q1	R2	P1
1	Q1	S1	N1
2	Q1	S1	N2
3	Q1	S1	P1
4	Q2	R1	N1
5	Q2	R1	N2
6	Q2	R1	P1
7	Q2	R2	N1
8	Q2	R2	N2
9	Q2	R2	P1

### Number of Half Bins from X<sub>5</sub>

#### Table 8: Number of Half Bins from X5 for HSMF-A2xx-xxxxx

X <sub>6</sub>	Color 1	Color 2
0	0	0
A	0	5
В	0	4
С	0	3
D	0	2
E	5	0
F	5	5
G	5	4
Н	5	3
J	5	2
К	4	0
L	4	5
М	4	4
Ν	4	3
Р	4	2
Q	3	0
R	3	5
S	3	4

### Table 8: Number of Half Bins from X5 for HSMF-A2xx-xxxxx

X <sub>6</sub>	Color 1	Color 2
Т	3	3
U	3	2
V	2	0
W	2	5
Х	2	4
Y	2	3
Z	2	2

**NOTE:** 0 represents full distribution.

#### Table 9: Number of Half Bins from X5 for HSMF-A3xx-xxxxx

X <sub>6</sub>	Color 1 (Red/ Red Orange)	Color 2 (Green)	Color 3 (Blue)
0	0	0	0
A	5	5	5
В	5	5	4
С	5	5	3
D	5	4	5
E	5	4	4
F	5	4	3
G	5	3	5
Н	5	3	4
J	5	3	3
К	4	5	5
L	4	5	4
М	4	5	3
Ν	4	4	5
Р	4	4	4
Q	4	4	3
R	4	3	5
S	4	3	4
Т	4	3	3
U	3	5	5
V	3	5	4
W	3	5	3
Х	3	4	5
Y	3	4	4
Z	3	4	3
1	3	3	5
2	3	3	4
3	3	3	3

**NOTE:** 0 represents full distribution.

### **Intensity Bin Limits**

Bin ID	Min. (mcd)	Max. (mcd)
J1	4.50	5.60
J2	5.60	7.20
K1	7.20	9.00
K2	9.00	11.20
L1	11.20	14.00
L2	14.00	18.00
M1	18.00	22.40
M2	22.40	28.50
N1	28.50	35.50
N2	35.50	45.00
P1	45.00	56.00
P2	56.00	71.50
Q1	71.50	90.00
Q2	90.00	112.50
R1	112.50	140.00
R2	140.00	180.00
S1	180.00	224.00
S2	224.00	285.00
T1	285.00	355.00
T2	355.00	450.00
U1	450.00	560.00
U2	560.00	715.00
V1	715.00	900.00
V2	900.00	1125.00

**NOTE:** Tolerance of each bin limit =  $\pm 10\%$ .

## Color Bin Select (X<sub>7</sub>)

Individual reel will contain parts from 1 full bin only.

#### Table 10: Color Bin Select for HSMF-A202-xxxxx, HSMF-A203xxxxx, HSMF-A212-xxxxx, HSMF-A222-xxxxx

X <sub>7</sub>	Color 1 (Red)	Color 2 (Emerald Green/ Yellow/Blue)
0	0	0
А	0	ABC
В	0	ABCD
С	0	ABCDE
D	0	BCD
E	0	BCDE
F	0	BCDEF

Broadcom

## Table 10: Color Bin Select for HSMF-A202-xxxxx, HSMF-A203-xxxxx, HSMF-A212-xxxxx, HSMF-A222-xxxxx

X <sub>7</sub>	Color 1 (Red)	Color 2 (Emerald Green/ Yellow/Blue)
G	0	CDE
Н	0	DEF
J	0	CDEF
К	0	AB
L	0	BC
М	0	CD
Ν	0	DE
Р	0	EF

**NOTE:** 0 represents full distribution.

 Table 11: Color Bin Select for HSMF-A201-xxxxx and HSMF-A211-xxxxx

x <sub>7</sub>	Color 1 (Red)	Color 2 (Yellow Green)
0	0	0
A	0	EFG
В	0	FGH
С	0	EF
D	0	FG
E	0	GH

**NOTE:** 0 represents full distribution.

Table 12: Color Bin Select for HSMF-A205-x	xxxx
--	------

X <sub>7</sub>	Color 1 (Yellow/ Amber/Orange)	Color 2 (Emerald Green/Blue)
0	0	0
A	ABC	ABC
В	BCD	ABC
С	CDE	ABC
D	ABC	BCD
E	BCD	BCD
F	CDE	BCD
G	ABC	CDE
Н	BCD	CDE
J	CDE	CDE
К	DEF	ABC
L	DEF	BCD
М	DEF	CDE
N	AB	AB

#### Table 12: Color Bin Select for HSMF-A205-xxxxx

x <sub>7</sub>	Color 1 (Yellow/ Amber/Orange)	Color 2 (Emerald Green/Blue)
Р	BC	AB
Q	CD	AB
R	DE	AB
S	AB	BC
Т	BC	BC
U	CD	BC
V	DE	BC
W	AB	CD
Х	BC	CD
Y	CD	CD
Z	DE	CD
1	AB	DE
2	BC	DE
3	CD	DE
4	DE	DE
5	EF	AB
6	EF	BC
7	EF	CD

**NOTE:** 0 represents full distribution.

## Table 13: Color Bin Select for HSMF-A204-xxxxx and HSMF-A206-xxxxx

X <sub>7</sub>	Color 1 (Yellow/ Amber/Orange)	Color 2 (Yellow Green)
0	0	0
A	ABC	EFG
В	BCD	EFG
С	CDE	EFG
D	DEF	EFG
E	ABC	FGH
F	BCD	FGH
G	CDE	FGH
Н	DEF	FGH
J	AB	EF
К	BC	EF
L	CD	EF
М	DE	EF
N	EF	EF
Р	AB	FG
Q	BC	FG
R	CD	FG

## Table 13: Color Bin Select for HSMF-A204-xxxxx and HSMF-A206-xxxxx

X <sub>7</sub>	Color 1 (Yellow/ Amber/Orange)	Color 2 (Yellow Green)
S	DE	FG
Т	EF	FG
U	AB	GH
V	BC	GH
W	CD	GH
Х	DE	GH
Y	EF	GH

**NOTE:** 0 represents full distribution.

#### Table 14: Color Bin Select for HSMF-A3xx-xxxxx

X <sub>7</sub>	Color 1	Color 2	Color 3
0	0	0	0
Α	0	0	ABC
В	0	0	BCD
С	0	0	AB
D	0	0	BC
E	0	0	CD
F	0	ABC	0
G	0	ABC	ABC
Н	0	ABC	BCD
J	0	ABC	AB
K	0	ABC	BC
L	0	ABC	CD
М	0	BCD	0
Ν	0	BCD	ABC
Ρ	0	BCD	BCD
Q	0	BCD	AB
R	0	BCD	BC
S	0	BCD	CD
Т	0	AB	ABC
U	0	AB	BCD
V	0	AB	AB
W	0	AB	BC
Х	0	AB	CD
Y	0	BC	ABC
Z	0	BC	BCD
1	0	BC	AB
2	0	BC	BC
3	0	BC	CD
4	0	CD	ABC

#### Table 14: Color Bin Select for HSMF-A3xx-xxxxx

X <sub>7</sub>	Color 1	Color 2	Color 3
5	0	CD	BCD
6	0	CD	AB
7	0	CD	BC
8	0	CD	CD

**NOTE:** 0 represents full distribution.

### **Color Bin Limits**

Blue	Min. (nm)	Max. (nm)
A	460.0	465.0
В	465.0	470.0
С	470.0	475.0
D	475.0	480.0

Green	Min. (nm)	Max. (nm)
A	515.0	520.0
В	520.0	525.0
С	525.0	530.0
D	530.0	535.0

Emerald Green	Min. (nm)	Max. (nm)
A	552.5	555.5
В	555.5	558.5
С	558.5	561.5
D	561.5	564.5

Yellow Green	Min. (nm)	Max. (nm)
E	564.5	567.5
F	567.5	570.5
G	570.5	573.5
Н	573.5	576.5

Amber/Yellow	Min. (nm)	Max. (nm)
A	582.0	584.5
В	584.5	587.0
С	587.0	589.5
D	589.5	592.0

Broadcom

Amber/Yellow	Min. (nm)	Max. (nm)
E	592.0	594.5
F	594.5	597.0

Orange	Min. (nm)	Max. (nm)
A	597.0	600.0
В	600.0	603.0
С	603.0	606.0
D	606.0	609.0
E	609.0	612.0

Red Orange	Min. (nm)	Max. (nm)
A	611.0	616.0
В	616.0	620.0

Red	Min. (nm)	Max. (nm)
Full Distribution		

## Packaging Option (X<sub>8</sub>X<sub>9</sub>)

X <sub>8</sub> X <sub>9</sub>	
J1	20 mA test current, Top Mount, 7-inch Reel

Broadcom, the pulse logo, Connecting everything, Avago Technologies, Avago, and the A logo are among the trademarks of Broadcom and/or its affiliates in the United States, certain other countries, and/or the EU.

Copyright © 2005–2019 Broadcom. All Rights Reserved.

The term "Broadcom" refers to Broadcom Inc. and/or its subsidiaries. For more information, please visit www.broadcom.com.

Broadcom reserves the right to make changes without further notice to any products or data herein to improve reliability, function, or design. Information furnished by Broadcom is believed to be accurate and reliable. However, Broadcom does not assume any liability arising out of the application or use of this information, nor the application or use of any product or circuit described herein, neither does it convey any license under its patent rights nor the rights of others.



