

1. Description

The STDP4328 is a high-speed DisplayPort dual mode concentrator IC that facilitates routing of multiple HDMI or DP audio-video streams on a single DP connector. This device is targeted for audio-video routing and multiplexer applications in digital signage, universal docking stations and high-end 4K2K cameras, recorders, etc. Enterprise universal docking station designs can make use of STDP4328 to route video from multiple sources such as notebooks, Smartphones, and tablets to share the desktop monitor space. High-end consumer products such as 4K2K cameras, recorders and players can make use of STDP4328 to transport a 4K2K 60 Hz uncompressed video and audio stream, which otherwise requires up to four HDMI connectors and cables. STDP4328 consists of two dual mode input ports and one dual mode output port, configurable as DisplayPort or HDMI/DVI. This device has VESA DP Standard Ver. 1.2a compliant receivers and transmitters supporting advanced features such as MST, HBR2, 3D formats, and GTC assist. Designs based on STDP4328 have the flexibility to offer either DP or HDMI/DVI connectors on its end product to interface with commercial and consumer video sources and displays. In addition, STDP4328 based products with a DisplayPort output connector are DP++ compliant which work with any HDMI or single link DVI displays through passive dongles (level translators).

The STDP4328 uses MegaChips' latest generation DisplayPort dual mode receiver and transmitter technology that supports both DisplayPort and TMDS signal format. In DisplayPort configuration, the device receives either SST or MST streams through the two input ports and combines them as one MST stream at the output port: in MST mode, it supports up to 8 AV streams. For example, it can receive two 2K x 2K 60 Hz streams on each of the input ports and send as one 4K2K 60 Hz SST or MST output to drive a 4K2K display. The DisplayPort receiver and transmitter supports HBR2 speed, a data rate of 5.4 Gbps per lane with a total bandwidth of 21.6 Gbps link rate. In HDMI mode, this device supports a link rate up to 3.2 Gbps that corresponds to a pixel rate of 320 MHz, adequate for supporting video resolution up to FHD 120 Hz including 3D formats. Two independent HDMI inputs can be converted into one DP MST output. The device is also capable of delivering deep color video up to 16-bits per color. It allows audio transport from the source to the desired audio rendering devices over the video output port or through the SPDIF port.

The STDP4328 supports RGB and YCC colorimetric formats with color depth of 16, 12, 10, and 8 bits. The device features the HDCP 1.3 content protection scheme with embedded keys for secure transmission of premium digital audio-video content. It also operates as an HDCP repeater for downstream sink.

The DDC ports allow the upstream source to access EDID and exchange MCCS commands with a downstream sink when the physical ports are either HDMI or DVI type. If both the upstream source and downstream sink are DP type, I2C transactions take place over the AUX CH. If the upstream is DP type and the downstream is either HDMI or DVI type, the device bridges DP AUX CH with downstream DDC port for all I2C-based transactions. The device has an on-chip microcontroller with SPI, UART, and I2C interface. It uses an external SPI Flash ROM for storing device configuration firmware. It has an I2C slave port for external host communication. Other system interface signals include general purpose IO for source, sink communication, detection, monitoring, etc.

2. Application overview

Figure 1. STDP4328 in universal docking station application




Figure 2. STDP4328 in digital signage application as DP/HDMI port expander





Figure 3. STDP4328 in camera/recorder/player application



3. Feature attributes

3.1 Input interface

- Dual DP++ interface featuring
 - DisplayPort Ver. 1.2a compliant receiver; supports eDP and MyDP
 - HDMI 1.4 compliant receiver
- Main link configuration
 - SST or MST (up to eight streams)
 - HBR2/HBR/RBR link rate
 - 1, 2, or 4 lanes
- AUX CH: 1 Mbps Manchester transaction format
- HPD: IRQ_HPD assertion
- Video: EDID 1.4 and CEA861 video timing and formats from 24 to 48 bits/pixel in RGB, YCC422, or YCC444 colorimetry
- Audio: DisplayPort 1.2a standard info frame packets and IEC60958/61937 type audio stream packets ranging from 16 to 24 bits/sample, 32 to 192 kHz sample rates
- HDMI link rate: 3.2 Gbps/data pair max

3.2 Output interface

- Single DP++ interfaces featuring
 - AC coupled DisplayPort Ver. 1.2a compliant transmitter: supports eDP
 - AC coupled HDMI 1.4 transmitter
- DP main link configuration
 - SST or MST (up to eight streams)
 - HBR2/HBR/RBR link rate
 - 1, 2, or 4 lanes
- AUX CH: Manchester transaction format
- HPD: IRQ_HPD assertion
- Video: EDID 1.4 and CEA861 video timing and formats from 24 to 48 bits/pixel in RGB, YCC422, or YCC444 colorimetry
- Audio: DisplayPort 1.2a standard info frame packets and IEC60958/61937 type audio stream packets ranging from 16 to 24 bits/sample, 32 to 192 kHz sample rates
- HDMI link rate: 3.2 Gbps/data pair max

3.3 Supported video timings

- 4K2K 60 Hz: 24 bits/pixel in DP 1.2a configuration
- 1920 x 1080 (FHD) 240 Hz, 24 bits/pixel
- All 3D formats defined in DP 1.2a and HDMI 1.4 standards
- All standard CEA861 timing formats

3.4 Supported audio timings

- All audio formats as specified in DP 1.2a and HDMI 1.4 standards
- SPDIF; 2-Ch LPCM, AC3, DTS, bit depth up to 24 bits, sample rate up to 192 kHz (applicable in DP SST/HDMI output use case)

3.5 Control channel interfaces

- AUX CH, DDC, I2C host interface, and UART (UART for test/debug purposes only)

3.6 HDCP 1.3 support

- Key sets for DP/HDMI RX and DP/HDMI TX integrated in one-time programmable ROM (OTP)
- Standalone HDCP repeater capability

3.7 Package

- 172 LFBGA (12 x 12 mm), 0.8 ball pitch

3.8 Power supply voltages

- 3.3 V I/O; 1.2 V core

3.9 ESD

- 2 KV HBM, 450 V CDM

4. Ordering information

Table 1. Order codes

Part number	Description
STDP4328-BA	172 LFBGA (12 x 12 mm)

5. Revision history

Table 2. Document revision history

Date	Revision	Changes
02-Oct-2012	1	Preliminary release.
08-May-2013	2	Cover page: Low power operation standby changed to 30 mW Added eDP references throughout. Deleted CEC feature throughout including in block diagrams. Added Figure 2. STDP4328 in digital signage application as DP/HDMI port expander. Ordering information section: Updated silicon revision in the table.
27-Jun-2013	3	Cover page: Deep color support YCC bullet updated. Section 3.9 ESD updated.
27-May-2014	4	Updated to comply with MegaChips documentation style/formatting.
20-Jun-2014	5	References to STDP4320 corrected.
15-Sep-2014	6	Updated footers and added copyright information to last page.

Notice

Semiconductor products may possibly experience breakdown or malfunction. Adequate care should be taken with respect to the safety design of equipment in order to prevent the occurrence of human injury, fire or social loss in the event of breakdown or malfunction of semiconductor products

The overview of operations and illustration of applications described in this document indicate the conceptual method of use of the semiconductor product and do not guarantee operability in equipment in which the product is actually used.

The names of companies and trademarks stated in this document are registered trademarks of the relevant companies.

MegaChips Co. provides no guarantees nor grants any implementation rights with respect to industrial property rights, intellectual property rights and other such rights belonging to third parties or/and MegaChips Co. in the use of products and of technical information including information on the overview of operations and the circuit diagrams that are described in this document.

The product described in this document may possibly be considered goods or technology regulated by the Foreign Currency and Foreign Trade Control Law. In the event such law applies, export license will be required under said law when exporting the product. This regulation shall be valid in Japan domestic.

In the event the intention is to use the product described in this document in applications that require an extremely high standard of reliability such as nuclear systems, aerospace equipment or medical equipment for life support, please contact the sales department of MegaChips Co. in advance.

All information contained in this document is subject to change without notice.

Copyright ©2014 MegaChips Corporation All rights reserved

MegaChips Corporation

Head Quarters

1-1-1 Miyahara, Yodogawa-ku Osaka 532-0003, Japan
TEL: +81-6-6399-2884

MegaChips Corporation

Tokyo Office

17-6 Ichiban-cho, Chiyoda-ku, Tokyo 102-0082, Japan
TEL: +81-3-3512-5080

MegaChips Corporation

Makuhari Office

1-3 Nakase Mihama-ku Chiba 261-8501, Japan
TEL: +81-43-296-7414

MegaChips Corporation

San Jose Office

2033 Gateway Place, Suite 400, San Jose, CA 95110 U.S.A.
TEL: +1-408-570-0555

MegaChips Corporation

India Branch

17th Floor, Concorde Block UB City,
Vittal Mallya Road, Bangalore 560-001, India
TEL: +91-80-4041-3999

MegaChips Corporation

Taiwan Branch

RM. B 2F, Worldwide House, No.129,
Min Sheng E. Rd., Sec. 3, Taipei 105, Taiwan
TEL: +886-2-2547-1297

MegaChips Corporation

Tainan Office

RM. 2, 8F, No.24, Da Qiao 2 Rd., Yong Kang Dist.,
Tainan 710, Taiwan
TEL: +886-6-302-2898

MegaChips Corporation

Zhunan Office

No.118, Chung-Hua Rd., Chu-Nan, Miao-Li 350, Taiwan
TEL: +886-37-666-156

MegaChips Corporation

Shenzhen Office

Room 6307, Office Tower, Shun Hing Square, 5002
Shen Nan Dong Road, Luohu District,
Shenzhen 518000, P. R. China
TEL: +86-755-3664-6990