



ABSOLUTE MAXIMUM RATINGS

Parameter	Limit	Unit
Supply Input Voltage (V_{IN})	- 0.3 to 6	V
Enable Input Voltage (V_{ON})	- 0.3 to 6	
Output Voltage (V_{OUT})	- 0.3 to $V_{IN} + 0.3$	
Maximum Continuous Switch Current (I_{MAX})	1.2	A
Maximum Pulsed Current (I_{DM}) V_{IN}	$V_{IN} \geq 2.5$ V	
	$V_{IN} < 2.5$ V	
ESD Rating (HBM)	4000	V
Junction Temperature (T_J)	- 40 to 150	°C
Thermal Resistance (θ_{JA}) ^a	6 pin PPAK SC75	°C/W
Power Dissipation (P_D) ^b	6 pin PPAK SC75	mW

Notes:

a. Device mounted with all leads and power pad soldered or welded to PC board.

b. Derate 11.1 mW/°C above $T_A = 70$ °C.

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating/conditions for extended periods may affect device reliability.

RECOMMENDED OPERATING RANGE

Parameter	Limit	Unit
Input Voltage Range (V_{IN})	1.8 to 5.5	V
Operating Temperature Range	- 40 to 85	°C

SPECIFICATIONS


Parameter	Symbol	Test Conditions Unless Specified V _{IN} = 5.0, T _A = - 40 °C to 85 °C (Typical values are at T _A = 25 °C)	Limits - 40 °C to 85 °C			Unit
			Min. ^a	Typ. ^b	Max. ^a	
SiP4282 All Versions						
Operating Voltage ^c	V _{IN}		1.8	-	5.5	V
Under Voltage Lockout	V _{UVLO}	V _{IN} Falling	1.0	1.4	1.8	
Under Voltage Lockout Hysteresis	V _{UVLO(hyh)}		-	250	-	mV
Quiescent Current	I _Q	ON/OFF = active	-	2.5	4	μA
Off Supply Current	I _{Q(OFF)}	ON/OFF = inactive, OUT = open	-	-	1	
Off Switch Current	I _{SD(OFF)}	ON/OFF = inactive, V _{OUT} = 0	-	-	1	
On-Resistance	R _{DS(on)}	V _{IN} = 5 V, T _A = 25 °C	-	140	230	mΩ
		V _{IN} = 4.2 V, T _A = 25 °C	-	150	250	
		V _{IN} = 3 V, T _A = 25 °C	-	175	290	
		V _{IN} = 1.8 V, T _A = 25 °C	-	300	480	
On-Resistance Temp-Coefficient	TC _{RDS}		-	2800	-	ppm/°C
ON/OFF Input Low Voltage	V _{IL}	V _{IN} = 2.7 V to 5.5 V ^d	-	-	0.8	V
ON/OFF Input High Voltage	V _{IH}	V _{IN} ≥ 1.8 to < 3.0	1.6	-	-	
		V _{IN} ≥ 3.0 to < 4.2	2	-	-	
		V _{IN} ≥ 4.2 to ≤ 5.5	2.4	-	-	
ON/OFF Input Leakage	I _{SINK}	V _{ON/OFF} = 5.5 V	-	-	1	μA
SiP4282-1 Version						
Output Turn-On Delay Time	t _{d(on)}	V _{IN} = 5 V, R _{LOAD} = 10 Ω, T _A = 25 °C	-	20	40	μs
Output Turn-On Rise Time	t _(on)	V _{IN} = 5 V, R _{LOAD} = 10 Ω, T _A = 25 °C	-	1000	1500	
Output Turn-Off Delay Time	t _{d(off)}	V _{IN} = 5 V, R _{LOAD} = 10 Ω, T _A = 25 °C	-	4	10	

**SPECIFICATIONS**

Parameter	Symbol	Test Conditions Unless Specified V _{IN} = 5.0, T _A = - 40 °C to 85 °C (Typical values are at T _A = 25 °C)	Limits - 40 °C to 85 °C			Unit
			Min. ^a	Typ. ^b	Max. ^a	
SiP4282-3 Version						
Output Turn-On Delay Time	t _{d(on)}	V _{IN} = 5 V, R _{LOAD} = 10 Ω, T _A = 25 °C	-	20	40	μs
Output Turn-On Rise Time	t _(on)	V _{IN} = 5 V, R _{LOAD} = 10 Ω, T _A = 25 °C	-	100	150	
Output Turn-Off Delay Time	t _{d(off)}	V _{IN} = 5 V, R _{LOAD} = 10 Ω, T _A = 25 °C	-	4	10	
Output Pull-Down Resistance	R _{PD}	ON/OFF = Inactive, T _A = 25 °C	-	150	250	Ω

Notes:

- a) The algebraic convention whereby the most negative value is a minimum and the most positive a maximum.
b) Typical values are for DESIGN AID ONLY, not guaranteed nor subject to production testing
c) Part requires minimum start-up of $V_{IN} \geq 2.0\text{ V}$ to ensure operation down to 1.8 V .
d) For V_{IN} outside this range consult typical ON/OFF threshold curve.

PIN CONFIGURATION

Bottom View

PPAK SC75-6 Package**PIN DESCRIPTION**

Pin Number PPAK SC75-6	Name	Function
1, 2	V_{IN}	This pin is the P-Channel MOSFET source connection. Bypass to ground through a $1\text{ }\mu\text{F}$ capacitor.
3	GND	Ground Connection
4	ON/OFF	Enable Input
5, 6	OUT	This pin is the P-Channel MOSFET drain connection. Bypass to ground through a $0.1\text{ }\mu\text{F}$ capacitor.

SELECTION GUIDE







Part Number	Slew Rate (typ)	Active Pull Down	Enable
SiP4282-1-T1-E3	1 ms	No	Active high
SiP4282-3-T1-E3	100 μs	Yes	Active high

ORDERING INFORMATION

Part Number	Marking	Temperature Range	Package
SiP4282DVP-1-T1-E3	L7XXX	- $40\text{ }^{\circ}\text{C}$ to $85\text{ }^{\circ}\text{C}$	PPAK SC75-6
SiP4282DVP-3-T1-E3	L9XXX		PPAK SC75-6


Notes:

XXX = Lot Code


TYPICAL CHARACTERISTICS internally regulated, 25 °C, unless otherwise noted**Quiescent Current vs. Input Voltage****Quiescent Current vs. Temperature** **$R_{\text{DS(ON)}}$ vs. Temperature** **$R_{\text{DS(ON)}}$ vs. Input Voltage****Off Switch Current vs. Temperature****ON/OFF Threshold vs. Input Voltage**




TYPICAL WAVEFORMS




SiP4282-1 Turn-On ($V_{IN} = 3$ V, $R_{LOAD} = 6$ Ω)







SiP4282-1 Turn-Off ($V_{IN} = 3$ V, $R_{LOAD} = 6$ Ω)




SiP4282-1 Turn-On ($V_{IN} = 5$ V, $R_{LOAD} = 10$ Ω)



SiP4282-1 Turn-Off ($V_{IN} = 5$ V, $R_{LOAD} = 10$ Ω)

TYPICAL WAVEFORMS**SiP4282-3 Turn-On ($V_{IN} = 3\text{ V}$, $R_{LOAD} = 6\ \Omega$)****SiP4282-3 Turn-Off ($V_{IN} = 3\text{ V}$, $R_{LOAD} = 6\ \Omega$)****SiP4282-3 Turn-On ($V_{IN} = 5\text{ V}$, $R_{LOAD} = 10\ \Omega$)****SiP4282-3 Turn-Off ($V_{IN} = 5\text{ V}$, $R_{LOAD} = 10\ \Omega$)**

BLOCK DIAGRAM



SiP4282 Functional Block Diagram

DETAILED DESCRIPTION

The SiP4282 is a P-Channel MOSFET power switches designed for high-side slew rate controlled load-switching applications. Once turned on, the slew-rate control circuitry is activated and current is ramped in a linear fashion until it reaches the level required for the output load condition. This is accomplished by first elevating the gate voltage of the MOSFET up to its threshold voltage and then by linearly increasing the gate voltage until the MOSFET becomes fully enhanced. At this point, the gate voltage is then quickly increased to the full input voltage to reduce $R_{DS(ON)}$ of the MOSFET switch and minimize any associated power losses.

The SiP4282-1 version has a modest 1 ms turn on slew rate feature, which significantly reduces in-rush current at turned on time and permits the load switch to be implemented with a small input capacitor, or no input capacitor at all, saving cost and space. In addition to a 100 μ s minimized slew rate, the SiP4282-3 features a shutdown output discharge circuit which is activated at shutdown (when the part is disabled through the ON/OFF pin) and discharges the output pin through a small internal resistor hence, turning off the load.

In instances where the input voltage falls below 1.4 V (typically) the under voltage lock-out circuitry protects the MOSFET switch from entering the saturation region or operation by shutting down the chip.

APPLICATION INFORMATION

Input Capacitor

While a bypass capacitor on the input is not required, a 1 μ F or larger capacitor for C_{IN} is recommended in almost all applications. The Bypass capacitor should be placed as physically close as possible to the SiP4282 to be effective in minimizing transients on the input. Ceramic capacitors are recommended over tantalum because of their ability to withstand input current surges from low impedance sources such as batteries in portable devices.

Output Capacitor

A 0.1 μ F capacitor or larger across V_{OUT} and GND is recommended to insure proper slew operation. C_{OUT} may be increased without limit to accommodate any load transient condition with only minimal affect on the SiP4282 turn on slew rate time. There are no ESR or capacitor type requirement.

Enable

The ON/OFF pin is compatible with both TTL and CMOS logic voltage levels.

Protection Against Reverse Voltage Condition

The P-channel MOSFET pass transistor has an intrinsic diode that is reversed biased when the input voltage is greater than the output voltage. Should V_{OUT} exceed V_{IN} , this intrinsic diode will become forward biased and allow excessive current to flow into the IC thru the V_{OUT} pin and potentially damage the IC device. Therefore extreme care should be taken to prevent V_{OUT} from exceeding V_{IN} .

In conditions where V_{OUT} exceeds V_{IN} a Schottky diode in parallel with the internal intrinsic diode is recommended to protect the SiP4282.

Thermal Considerations

The SiP4282 is designed to maintain a constant output load current. Due to physical limitations of the layout and assembly of the device the maximum switch current is 1.2 A, as stated in the ABS MAX table. However, another limiting characteristic for the safe operating load current is the thermal power dissipation of the package. To obtain the highest power dissipation (and a thermal resistance of 90 °C/W) the power pad of the device should be connected to a heat sink on the printed circuit board.

The maximum power dissipation in any application is dependant on the maximum junction temperature, $T_{J(MAX)} = 125$ °C, the junction-to-ambient thermal resistance for the SC-75 PPAK package, $\theta_{J-A} = 90$ °C/W, and the ambient temperature, T_A , which may be formulaically expressed as:

$$P (max) = \frac{T_J (max) - T_A}{\theta_{J-A}} = \frac{125 - T_A}{90}$$

It then follows that, assuming an ambient temperature of 70 °C, the maximum power dissipation will be limited to about 610 mW.

So long as the load current is below the 1.2 A limit, the maximum continuous switch current becomes a function two things: the package power dissipation and the $R_{DS(ON)}$ at the ambient temperature.

As an example let us calculate the worst case maximum load current at $T_A = 70$ °C. The worst case $R_{DS(ON)}$ at 25 °C occurs at an input voltage of 1.8 V and is equal to 480 mΩ. The $R_{DS(ON)}$ at 70 °C can be extrapolated from this data using the following formula

$$R_{DS(ON)} (at 70\text{ °C}) = R_{DS(ON)} (at 25\text{ °C}) \times (1 + T_C \times \Delta T)$$

Where T_C is 3300 ppm/°C. Continuing with the calculation we have

$$R_{DS(ON)} (at 70\text{ °C}) = 480\text{ m}\Omega \times (1 + 0.0033 \times (70\text{ °C} - 25\text{ °C})) = 551\text{ m}\Omega$$

The maximum current limit is then determined by

$$I_{LOAD (max)} < \sqrt{\frac{P (max)}{R_{DS(ON)}}}$$

which in case is 1.05 A. Under the stated input voltage condition, if the 1.05 A current limit is exceeded the internal die temperature will rise and eventually, possibly damage the device.



Disclaimer

All product specifications and data are subject to change without notice.

Vishay Intertechnology, Inc., its affiliates, agents, and employees, and all persons acting on its or their behalf (collectively, "Vishay"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained herein or in any other disclosure relating to any product.

Vishay disclaims any and all liability arising out of the use or application of any product described herein or of any information provided herein to the maximum extent permitted by law. The product specifications do not expand or otherwise modify Vishay's terms and conditions of purchase, including but not limited to the warranty expressed therein, which apply to these products.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document or by any conduct of Vishay.

The products shown herein are not designed for use in medical, life-saving, or life-sustaining applications unless otherwise expressly indicated. Customers using or selling Vishay products not expressly indicated for use in such applications do so entirely at their own risk and agree to fully indemnify Vishay for any damages arising or resulting from such use or sale. Please contact authorized Vishay personnel to obtain written terms and conditions regarding products designed for such applications.

Product names and markings noted herein may be trademarks of their respective owners.