

Absolute Maximum Ratings

Absolute Maximum Ratings indicate sustained limits beyond which damage to the device may occur. All voltage parameters are absolute voltages referenced to COM. The Thermal Resistance and Power Dissipation ratings are measured under board mounted and still air conditions. Additional information is shown in Figures 28 through 35.

Symbol	Definition	Min.	Max.	Units
V_B	High Side Floating Supply Voltage	-0.3	625	V
V_S	High Side Floating Supply Offset Voltage	$V_B - 25$	$V_B + 0.3$	
V_{HO}	High Side Floating Output Voltage	$V_S - 0.3$	$V_B + 0.3$	
V_{CC}	Low Side Fixed Supply Voltage	-0.3	25	
V_{LO}	Low Side Output Voltage	-0.3	$V_{CC} + 0.3$	
V_{DD}	Logic Supply Voltage	-0.3	$V_{SS} + 25$	
V_{SS}	Logic Supply Offset Voltage	$V_{CC} - 25$	$V_{CC} + 0.3$	
V_{IN}	Logic Input Voltage (HIN, LIN & SD)	$V_{SS} - 0.3$	$V_{DD} + 0.3$	
dV_S/dt	Allowable Offset Supply Voltage Transient (Figure 2)	—	50	V/ns
P_D	Package Power Dissipation @ $T_A \leq +25^\circ\text{C}$ (14 Lead DIP)	—	1.6	W
	(16 Lead SOIC)	—	1.25	
R_{THJA}	Thermal Resistance, Junction to Ambient (14 Lead DIP)	—	75	$^\circ\text{C}/\text{W}$
	(16 Lead SOIC)	—	100	
T_J	Junction Temperature	—	150	$^\circ\text{C}$
T_S	Storage Temperature	-55	150	
T_L	Lead Temperature (Soldering, 10 seconds)	—	300	

Recommended Operating Conditions

The Input/Output logic timing diagram is shown in Figure 1. For proper operation the device should be used within the recommended conditions. The V_S and V_{SS} offset ratings are tested with all supplies biased at 15V differential. Typical ratings at other bias conditions are shown in Figures 36 and 37.

Symbol	Definition	Min.	Max.	Units
V_B	High Side Floating Supply Absolute Voltage	$V_S + 10$	$V_S + 20$	V
V_S	High Side Floating Supply Offset Voltage	Note 1	600	
V_{HO}	High Side Floating Output Voltage	V_S	V_B	
V_{CC}	Low Side Fixed Supply Voltage	10	20	
V_{LO}	Low Side Output Voltage	0	V_{CC}	
V_{DD}	Logic Supply Voltage	$V_{SS} + 3$	$V_{SS} + 20$	
V_{SS}	Logic Supply Offset Voltage	-5 (Note 2)	5	
V_{IN}	Logic Input Voltage (HIN, LIN & SD)	V_{SS}	V_{DD}	
T_A	Ambient Temperature	-40	125	$^\circ\text{C}$

Note 1: Logic operational for V_S of -5 to +600V. Logic state held for V_S of -5V to $-V_{BS}$. (Please refer to the Design Tip DT97-3 for more details).

Note 2: When $V_{DD} < 5\text{V}$, the minimum V_{SS} offset is limited to $-V_{DD}$.

Dynamic Electrical Characteristics


V_{BIAS} (V_{CC} , V_{BS} , V_{DD}) = 15V, C_L = 1000 pF, T_A = 25°C and V_{SS} = COM unless otherwise specified. The dynamic electrical characteristics are measured using the test circuit shown in Figure 3.

Symbol	Definition	Figure	Min.	Typ.	Max.	Units	Test Conditions
t_{on}	Turn-On Propagation Delay	7	—	125	180	ns	V_S = 0V
t_{off}	Turn-Off Propagation Delay	8	—	105	160		V_S = 600V
t_{sd}	Shutdown Propagation Delay	9	—	105	160		V_S = 600V
t_r	Turn-On Rise Time	10	—	80	130		
t_f	Turn-Off Fall Time	11	—	40	65		
MT	Delay Matching, HS & LS Turn-On/Off	—	—	—	30		

Static Electrical Characteristics



V_{BIAS} (V_{CC} , V_{BS} , V_{DD}) = 15V, T_A = 25°C and V_{SS} = COM unless otherwise specified. The V_{IN} , V_{TH} and I_{IN} parameters are referenced to V_{SS} and are applicable to all three logic input leads: HIN, LIN and SD. The V_O and I_O parameters are referenced to COM and are applicable to the respective output leads: HO or LO.

Symbol	Definition	Figure	Min.	Typ.	Max.	Units	Test Conditions
V_{IH}	Logic "1" Input Voltage	12	9.5	—	—	V	
V_{IL}	Logic "0" Input Voltage	13	—	—	6.0		
V_{OH}	High Level Output Voltage, $V_{BIAS} - V_O$	14	—	—	100	mV	I_O = 0A
V_{OL}	Low Level Output Voltage, V_O	15	—	—	100		I_O = 0A
I_{LK}	Offset Supply Leakage Current	16	—	—	50	μA	$V_B = V_S = 600V$
I_{QBS}	Quiescent V_{BS} Supply Current	17	—	25	60		$V_{IN} = 0V$ or V_{DD}
I_{QCC}	Quiescent V_{CC} Supply Current	18	—	80	180		$V_{IN} = 0V$ or V_{DD}
I_{QDD}	Quiescent V_{DD} Supply Current	19	—	2.0	5.0		$V_{IN} = 0V$ or V_{DD}
I_{IN+}	Logic "1" Input Bias Current	20	—	20	40		$V_{IN} = V_{DD}$
I_{IN-}	Logic "0" Input Bias Current	21	—	—	1.0		$V_{IN} = 0V$
V_{BSUV+}	V_{BS} Supply Undervoltage Positive Going Threshold	22	7.4	8.5	9.6	V	
V_{BSUV-}	V_{BS} Supply Undervoltage Negative Going Threshold	23	7.0	8.1	9.2		
V_{CCUV+}	V_{CC} Supply Undervoltage Positive Going Threshold	24	7.6	8.6	9.6		
V_{CCUV-}	V_{CC} Supply Undervoltage Negative Going Threshold	25	7.2	8.2	9.2		
I_{O+}	Output High Short Circuit Pulsed Current	26	200	250	—	mA	$V_O = 0V$, $V_{IN} = V_{DD}$ $PW \leq 10 \mu s$
I_{O-}	Output Low Short Circuit Pulsed Current	27	420	500	—		$V_O = 15V$, $V_{IN} = 0V$ $PW \leq 10 \mu s$

Functional Block Diagram**Lead Definitions**

Symbol	Description
V _{DD}	Logic supply
HIN	Logic input for high side gate driver output (HO), in phase
SD	Logic input for shutdown
LIN	Logic input for low side gate driver output (LO), in phase
V _{SS}	Logic ground
V _B	High side floating supply
HO	High side gate drive output
V _S	High side floating supply return
V _{CC}	Low side supply
LO	Low side gate drive output
COM	Low side return

Lead Assignments

 <table border="1"> <tr><td>8</td><td></td><td>HO</td><td>7</td></tr> <tr><td>9</td><td>VDD</td><td>VB</td><td>6</td></tr> <tr><td>10</td><td>HIN</td><td>VS</td><td>5</td></tr> <tr><td>11</td><td>SD</td><td></td><td>4</td></tr> <tr><td>12</td><td>LIN</td><td>VCC</td><td>3</td></tr> <tr><td>13</td><td>VSS</td><td>COM</td><td>2</td></tr> <tr><td>14</td><td></td><td>LO</td><td>1</td></tr> </table> <p>14 Lead PDIP w/o lead 4 IR2112-1</p>	8		HO	7	9	VDD	VB	6	10	HIN	VS	5	11	SD		4	12	LIN	VCC	3	13	VSS	COM	2	14		LO	1	 <table border="1"> <tr><td>8</td><td></td><td>HO</td><td>7</td></tr> <tr><td>9</td><td>VDD</td><td>VB</td><td>6</td></tr> <tr><td>10</td><td>HIN</td><td>VS</td><td></td></tr> <tr><td>11</td><td>SD</td><td></td><td></td></tr> <tr><td>12</td><td>LIN</td><td>VCC</td><td>3</td></tr> <tr><td>13</td><td>VSS</td><td>COM</td><td>2</td></tr> <tr><td>14</td><td></td><td>LO</td><td>1</td></tr> </table> <p>14 Lead PDIP w/o leads 4 & 5 IR2112-2</p>	8		HO	7	9	VDD	VB	6	10	HIN	VS		11	SD			12	LIN	VCC	3	13	VSS	COM	2	14		LO	1
8		HO	7																																																						
9	VDD	VB	6																																																						
10	HIN	VS	5																																																						
11	SD		4																																																						
12	LIN	VCC	3																																																						
13	VSS	COM	2																																																						
14		LO	1																																																						
8		HO	7																																																						
9	VDD	VB	6																																																						
10	HIN	VS																																																							
11	SD																																																								
12	LIN	VCC	3																																																						
13	VSS	COM	2																																																						
14		LO	1																																																						
Part Number																																																									

IR2112(-1-2)(S)PbF

International
IR Rectifier




Figure 1. Input/Output Timing Diagram




Figure 2. Floating Supply Voltage Transient Test Circuit




Figure 3. Switching Time Test Circuit




Figure 4. Switching Time Waveform Definition




Figure 5. Shutdown Waveform Definitions




Figure 6. Delay Matching Waveform Definitions




Figure 7A. Turn-On Time vs. Temperature




Figure 7B. Turn-On Time vs. V_{CC}/V_{BS} Supply Voltage




Figure 7C. Turn-On Time vs. V_{DD} Supply Voltage




Figure 8A. Turn-Off Time vs. Temperature




Figure 8B. Turn-Off Time vs. V_{CC}/V_{BS} Supply Voltage




Figure 8C. Turn-Off Time vs. V_{DD} Supply Voltage

IR2112(-1-2)(S)PbF

International
IR Rectifier




Figure 9A. Shutdown Time vs. Temperature




Figure 9B. Shutdown Delay Time vs. V_{CC}/V_{BS} Supply Voltage




Figure 9C. Shutdown Time vs. V_{DD} Supply Voltage




Figure 10A. Turn-On Rise Time vs. Temperature




Figure 10B. Turn-On Rise Time vs. Voltage




Figure 11A Turn-On Fall Time vs. Temperature




Figure 11B. Turn-Off Fall Time vs. Voltage




Figure 12A. Logic "1" Input Threshold vs. Temperature




Figure 12B. Logic "1" Input Threshold vs. Voltage




Figure 13A. Logic "0" Input Threshold vs. Temperature




Figure 13B. Logic "0" Input Threshold vs. Voltage




Figure 14A. High Level Output vs. Temperature

IR2112(-1-2)(S)PbF

International
IR Rectifier




Figure 14B. High Level Output vs. Voltage




Figure 15A. Low Level Output vs. Temperature




Figure 15B. Low Level Output vs. Voltage




Figure 16A. Offset Supply Current vs. Temperature




Figure 16B. Offset Supply Current vs. Voltage




Figure 17A. V_{BS} Supply Current vs. Temperature




Figure 17B. V_{BS} Supply Current vs. Voltage




Figure 18A. V_{CC} Supply Current vs. Temperature




Figure 18B. V_{CC} Supply Current vs. Voltage




Figure 19A. V_{DD} Supply Current vs. Temperature




Figure 19B. V_{DD} Supply Current vs. V_{DD} Voltage




Figure 20A. Logic "1" Input Current vs. Temperature

IR2112(-1-2)(S)PbF

International
IR Rectifier




Figure 20B. Logic "1" Input Current vs. V_{DD} Voltage




Figure 21B. Logic "0" Input Current vs. V_{DD} Voltage




Figure 23. V_{BS} Undervoltage Lockout (-) vs. Temperature




Figure 21A. Logic "0" Input Current vs. Temperature




Figure 22. V_{BS} Undervoltage Lockout (+) vs. Temperature




Figure 24. V_{CC} Undervoltage Lockout (-) vs. Temperature




Figure 25. Vcc Undervoltage (-) vs. Temperature




Figure 26A. Output Source Current vs. Temperature




Figure 26B. Output Source Current vs. Voltage




Figure 27A. Output Sink Current vs. Temperature




Figure 27B. Output Sink Current vs. Voltage

IR2112(-1-2)(S)PbF

International
IR Rectifier




Figure 28. IR2112 T_J vs. Frequency (IRFBC20)
 $R_{GATE} = 33\Omega$, $V_{CC} = 15V$




Figure 29. IR2112 T_J vs. Frequency (IRFBC30)
 $R_{GATE} = 22\Omega$, $V_{CC} = 15V$




Figure 30. IR2112 T_J vs. Frequency (IRFBC40)
 $R_{GATE} = 15\Omega$, $V_{CC} = 15V$




Figure 31. IR2112 T_J vs. Frequency (IRFPE50)
 $R_{GATE} = 10\Omega$, $V_{CC} = 15V$




Figure 32. IR2112S T_J vs. Frequency (IRFBC20)
 $R_{GATE} = 33\Omega$, $V_{CC} = 15V$




Figure 33. IR2112S T_J vs. Frequency (IRFBC30)
 $R_{GATE} = 22\Omega$, $V_{CC} = 15V$




Figure 34. IR2112S T_J vs. Frequency (IRFBC40)
R_{GATE} = 15Ω, V_{CC} = 15V




Figure 35. IR2112S T_J vs. Frequency (IRFPE50)
R_{GATE} = 10Ω, V_{CC} = 15V




Figure 36. Maximum Vs Negative Offset vs.
V_{BS} Supply Voltage








Figure 37. Maximum V_{SS} Positive Offset vs.
V_{CC} Supply Voltage


IR2112(-1-2)(S)PbF

International
IR Rectifier

Case outline





LEADFREE PART MARKING INFORMATION**ORDER INFORMATION****Part only available Leadfree**

14-Lead PDIP IR2112 order IR2112PbF
14-Lead PDIP IR2112-1 order IR2112-1PbF
14-Lead PDIP IR2112-2 order IR2112-2PbF
16-Lead SOIC IR2112S order IR2112SPbF

International
IR Rectifier

IR WORLD HEADQUARTERS: 233 Kansas St., El Segundo, California 90245 Tel: (310) 252-7105
This product has been qualified per industrial level
Data and specifications subject to change without notice. 3/23/2005