


Fig. 5 Static Drain-Source On-Resistance vs. Drain Current






Fig. 4 Static Drain-Source On-Resistance vs. Drain Current




Fig. 6 Static Drain-Source On-Resistance vs. Gate-Source Voltage






Fig. 7 Static Drain-Source On-State Resistance vs. Ambient Temperature





Fig. 9 Reverse Drain Current vs. Source-Drain Voltage






Fig. 8 Reverse Drain Current vs. Source-Drain Voltage




Fig.10 Forward Transfer Admittance vs. Drain Current




### Ordering Information (Note 6)

Part Number	Case	Packaging
DMN5L06DMK-7	SOT-26	3000/Tape & Reel

Notes: 6. For packaging details, go to our website at http://www.diodes.com/datasheets/ap02007.pdf.

## **Marking Information**




DAB = Marking Code YM = Date Code Marking Y = Year ex: T = 2006 M = Month ex: 9 = September

Date Code Key


Year	200	6	2007		2008	20	09	2010		2011	2	2012
Code	Т		U		V	V	٧	Χ		Υ		Z
Month	Jan	Feb	Mar	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec
Code	1	2	3	4	5	6	7	8	9	0	N	D

## **Package Outline Dimensions**



SOT-26					
Dim	Min	Max	Тур		
Α	0.35	0.50	0.38		
В	1.50	1.70	1.60		
С	2.70	3.00	2.80		
D	_	_	0.95		
F	-	-	0.55		
Н	2.90	3.10	3.00		
J	0.013	0.10	0.05		
K	1.00	1.30	1.10		
L	0.35	0.55	0.40		
M	0.10	0.20	0.15		
α	0°	8°	_		
All Dimensions in mm					

# **Suggested Pad Layout**



Dimensions	Value (in mm)
Z	3.20
G	1.60
X	0.55
Υ	0.80
С	2.40
E	0.95

### IMPORTANT NOTICE

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to any product herein. Diodes Incorporated does not assume any liability arising out of the application or use of any product described herein; neither does it convey any license under its patent rights, nor the rights of others. The user of products in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on our website, harmless against all damages.

### LIFE SUPPORT

Diodes Incorporated products are not authorized for use as critical components in life support devices or systems without the expressed written approval of the President of Diodes Incorporated.