SATCR-1

FEATURES

- Wide input and wide output frequency ranges (950 MHz to 2150 MHz)
- Four programmable conversion gains
- Fully integrated synthesizer
- RF tone generator for installation loss calibration and for system signalling
- Programmable switch matrix control pins
- System noise figure: 5 dB (typ.)
- Single supply: 3.0 V
- Low power consumption: 90 mA (typ.)
- I2C bus control
- QFN36 package (6 x 6 mm)

APPLICATIONS

- DDBS low-noise block converters
- RF band translation switcher boxes
- Reuse of terrestrial cable for satellite signals
- Provides single-cable capability for:
 - DVR applications
 - multiple STBs/receivers
 - multi-switching for apartment blocks.

PART NUMBERING

Table 1. Order codes

Part Number	Description
SaTCR-1	Satellite channel router
SaTCR-1 Eval	Evaluation board

REVISION HISTORY

Downloaded from Arrow.com.

Table 2. Revision history

Date	Revision	Description of Changes
October 2004	2	Updated diagram, history added, color removed, CCS template applied.
May 2004	1	Initial release

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

The ST logo is a registered trademark of STMicroelectronics.
All other names are the property of their respective owners

© 2004 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

www.st.com

2/2